3. Electrical Parts List

Location no	Code no.	Description	Specifiation	Remarks

***** MAX-WB630/WB650 PARTS LIST *****

	AH26-00175A	TRANS POWER;-,MAX-WB630,-,-,115/230V,50HZ	MAX-WB630
	AH26-00176A	TRANS POWER;-,MAX-WB630,-,-,127V,60HZ	MAX-WB630
	AH26-00177A	TRANS POWER;-,MAX-WB630,-,-,120/240V,50/60HZ	MAX-WB630
	AH26-00178A	TRANS POWER;-,MAX-WB630,-,-,230/254V,50HZ	MAX-WB630
	AH26-00179A	TRANS POWER;-,MAX-WB630,-,-,220V,60HZ	MAX-WB630
	AH26-00170A	TRANS POWER;-,MAX-WB650,-,-,115/230V,50HZ	MAX-WB650
	AH26-00171A	TRANS POWER;-,MAX-WB650,-,-,127V,60HZ	MAX-WB650
	AH26-00172A	TRANS POWER;-,MAX-WB650,-,-,120/240V,50/60HZ	MAX-WB650
	AH26-00173A	TRANS POWER;-,MAX-WB650,-,-,230/254V,50HZ	MAX-WB650
	AH26-00174A	TRANS POWER;-,MAX-WB650,-,-,220V,60HZ	MAX-WB650
	AH39-00257A	POWER CORD;CP2,250V,2.5A,1830MM	CP2(VDE)
	AH39-00258Q	POWER CORD;BS,250V,2.5A,1830MM	BS(U.K)
	AH39-00257D	POWER CORD;KS,250V,2.5A,1830MM	KS(KOREA)
	AH39-00258H	POWER CORD;UL/CSA,125V,10A,1830MM	EP2(UL/CSA)
	AH39-00258H	POWER CORD;IRAM,AP2,125V,10A,1830MM	AP2(ARGENTINA)
	AH39-00258B	POWER CORD;SAA,AP2,125V,17.5A,1830MM	AP2(AUSTRALIA)
	AH40-00008A	TUNER-PACK ASSY;RDS,FM/MW/LW	RDS(EU)
	AH40-00009A	TUNER-PACK ASSY;OIRT,FM/MW/LW	OIRT(RUSSIA)
	AH40-00010A	TUNER-PACK ASSY;FM/AM T-BAND	
	AH40-00012A	TUNER-PACK ASSY;FM/MW/LW	L-BAND
	AH40-00013A	TUNER-PACK ASSY;FM/MW/SW1/SW2	SW-BAND
	AH42-20001P	ANT LOOP;-,KS971120-01,18.5UH##10%,-	COMMON
	AH59-00134M	REMOCON-ASSY;MAX-WB630,WB650,27KEY	LATIN AMERICA
	AH59-00134L	REMOCON-ASSY;MAX-WB630,WB650,27KEY	EXCEPT LATIN AMERICA

AH59-00162A CD-MECHA/DECK ASSY;CMS300-V MAX-WB630/WB650

	AH97-00900M	**ASSY-CA'DECK;-,RCD495/695/ST-68,ASSY CA'**
	3809-001188	CABLE-FLAT;30V,80C,240mm,16P,1.25mm,UL28
	6002-000396	SCREW-TAPPING;BH,+,2,M2,L5,ZPC(WHT),SWCH
	AH39-00021A	LEAD CONNECTOR ASSY;UL1533#28,300MM,-,-,
	AH39-20002D	LEAD CONNECTOR ASSY;5264,-,3P,300MM,2970
	AH59-00075A	DECK;ADR246AMW,1A/RVS,-,-,DC12V,-,-

AH92-00922A ASSY PCB-CD;G3HI-3CD,3.5S

WIC402	1003-001162	IC-MOTOR DRIVER;KA3082,SIP,10PIN,25MIL,D
WIC401	1003-001162	IC-MOTOR DRIVER;KA3082,SIP,10PIN,25MIL,D
X201	2802-000211	RESONATOR-CERAMIC;16.93MHz,0.5%,TP,10.0x
CW103	3708-001131	CONNECTOR-FPC/FFC/PIC;5P,1.25mm,STRAIGHT
CW101	3708-001252	CONNECTOR-FPC/FFC/PIC;16P,1mm,STRAIGHT-F
CW105	3708-001438	CONNECTOR-FPC/FFC/PIC;22P,1.25mm,ANGLE,S
CW107	3711-000906	CONNECTOR-HEADER;BOX,3P,1R,2mm,ANGLE,SN
CW104	3711-003379	CONNECTOR-HEADER;NOWALL,3P,1R,2.5mm,STRA
CW106	AH39-00060A	LEAD CONNECTOR ASSY;-,51015-08,51004-08,
CW102	AH39-20561P	LEAD CONNECTOR ASSY;-,5295,PHR,6P,150mm,
D301	0402-000151	DIODE-RECTIFIER;1N5392,100V,1.5A,DO-15,T
ZD301	0403-000344	DIODE-ZENER;UZ3.9B,3.9V,3.7-4.1V,500mW,D
ZD402	0403-000352	DIODE-ZENER;UZ4.7BM,4.7V,4.4-5.0V,500mW,
ZD401	0403-000361	DIODE-ZENER;UZ6.2BSB,6.2V,5.99-6.24V,500
Q302	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,
Q101	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,
Q301	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,
IC201	0904-001524	IC-DSP;5L9290,-,QFP,48P,472MIL,16.934
IC301	1003-000179	IC-MOTOR DRIVER;KA9258D,SOP,28P,-,SINGLE
IC101	1204-001799	IC-ASP;KB9226,LQFP,48P,393MIL,PLASTIC
R117	2001-000331	R-CARBON;12Kohm,5%,1/8W,AA,TP,1.8x3.2mm
R810	2001-000362	R-CARBON;150ohm,5%,1/8W,AA,TP,1.8x3.2mm
R803	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm
R302	2001-001006	R-CARBON;82ohm,5%,1/8W,AA,TP,1.8x3.2mm
R114	2007-000001	R-CHIP;68KOHM,5%,1/10W,DA,TP,2012
J2	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012
J13	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012
J10	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012
J1	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012
J8	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012
J9	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012
MJ1	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012
J7	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012
J5	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012
J4	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012
J3	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012
R501R	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012
R501L	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012
R502R	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012
R502L	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012
R201	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012
R809	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
R133	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
R132	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
MR3	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
MR2	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
R108	2007-000308	R-CHIP;10OHM,5%,1/10W,DA,TP,2012
R124	2007-000338	R-CHIP;120KOHM,5%,1/10W,DA,TP,2012
R125	2007-000338	R-CHIP;120KOHM,5%,1/10W,DA,TP,2012
R110	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012
R121	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012
R113	2007-000444	R-CHIP;180KOHM,5%,1/10W,DA,TP,2012
R209	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012
R804	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012
R805	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012
R806	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012
R811	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012
R204	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012
R205	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012
R206	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012
R207	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012
R208	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012
R204	2007-000477	R-CHIP;1MOHM,5%,1/10W,DA,TP,2012
R118	2007-000477	R-CHIP;1MOHM,5%,1/10W,DA,TP,2012
R116	2007-000546	R-CHIP;20KOHM,5%,1/10W,DA,TP,2012
R210	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012
R128	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012
R808	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012
R807	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012
DR2	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012
DR1	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012
R813	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012
R129	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012
R123	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012
R126	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012
R120	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012
R104	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012
R103	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012
R102	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012
R101	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012
R115	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012
R112	2007-001195	R-CHIP;820KOHM,5%,1/10W,DA,TP,2012
R127	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012
R119	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012
R106	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012
R105	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012
R107	2007-001216	R-CHIP;82OHM,5%,1/10W,DA,TP,2012
R301	2008-000140	R-FUSIBLE;2.2ohm,5%,1/2W,AA,TP,3.5x9.4mm
C806	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.
C805	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.
C804	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.
C603A	2202-000780	C-CERAMIC,MLC-AXIAL;100nF,+80-20%,50V,Y5
C113	2202-000780	C-CERAMIC,MLC-AXIAL;100nF,+80-20%,50V,Y5
C131	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012
C132	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012
C204	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012
C205	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012
C211	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012
C130	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012
C115	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012
C116	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012
C118	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012
C124	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012
C129	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012
C218	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
C216	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
C214	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
C402	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
C401	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
C305	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
C304	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
C134	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
C121	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
C105	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
C103	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
C213	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
C209	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
C207	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
C126	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,2012
C127	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012
C803	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012
C119	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012
C128	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012
C125	2203-000840	C-CERAMIC,CHIP;0.39nF,5%,50V,NP0,TP,2012
C208	2203-000858	C-CERAMIC,CHIP;0.039nF,5%,50V,NP0,TP,201
C111	2203-000892	C-CERAMIC,CHIP;4.7NF,10%,50V,X7R,TP,2012
C112	2203-000892	C-CERAMIC,CHIP;4.7NF,10%,50V,X7R,TP,2012
C124A	2203-001064	C-CERAMIC,CHIP;56NF,10%,50V,NPO,TP,2012
C106	2203-001137	C-CERAMIC,CHIP;68nF,+80-20%,50V,Y5V,TP,2
C122	2203-001137	C-CERAMIC,CHIP;68nF,+80-20%,50V,Y5V,TP,2
C203	2203-001223	C-CERAMIC,CHIP;0.82nF,10%,50V,X7R,TP,201
C502R	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012
C502L	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012
C117	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012

Location no	Code no.	Description	Specifiation	Remarks
C102	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012		
C104	2203-001551	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,2012		
C202	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,201		
C201	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,201		
C215	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C217	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C302	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C303	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C212	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C101	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C107	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C108	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C133	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C123	2401-000419	C-AL;10UF,20%,16V,GP,5*11,5MM,TP		
C301	2401-001102	C-AL;330uF,20%,16V,GP,TP,8x11.5mm,5		
C114	2401-001625	C-AL;6.8uF,20%,50V,GP,TP,5x11,5		
C501R	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm		
C501L	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm		
C120	2401-001968	C-AL;470nF,20%,50V,GP,TP,5x11mm,5mm		
C135	2401-001968	C-AL;470nF,20%,50V,GP,TP,5x11mm,5mm		
C801	2401-002183	C-AL;220uF,20%,16V,GP,TP,8x9,5mm		
WIC801	AC14-12001G	IC;KA78L05,T,-		
	AH41-00282B	PCB—CD MAIN;G3HI-3CD;G3HI-3CD;CD MAIN,P		
	AJ59-20150F	**DECK-LDP;CVM55R2/EXP,-,-,-,-**		**COMMON**
	3405-000101	SWITCH-MICRO;1.6V,1A,70gf,SPST		
	3710-000544	CONNECTOR-SOCKET;42140-2203 3P ,1R,2.5MM		
	3711-000826	CONNECTOR-HEADER;BOX,2P,1R,2mm,ANGLE,SN		
	AH31-10021A	MOTOR-DC;RF-500TB,9VDC/130mA,		
	AH31-12001A	MOTOR-LOADING;FF-030PN-09210		
	AH91-60150C	**ASSY CDP DECK;CMS-D73SG6(U)/JVC,CMS-300D**		**COMMON**
	3409-001078	SWITCH-LEAF;16Vdc,500mA,10gf,SPST		
	AH30-00007A	PICK UP;SOH-AD3,-,-,-,100*80*45,D73SG6		
	AH81-00614A	A/S-SHAFT-PU;-,METAL,-,-,-,-,-		
	AH81-00614B	A/S-SCREW;-,METAL,AJ60-00601D,-,-,-,-		
	AH81-00614C	A/S-SCREW;-,METAL,6003-000294,-,-,-,-		
	AH81-00614D	A/S-WASHER;-,PBT,AJ60-00608A,-,-,-,-		
	AH81-00614E	A/S-GEAR(C);-,PBT,AJ66-00006A,-,-,-,-		
	AH81-00614F	A/S-GEAR(B);-,PBT,AJ66-00005A,-,-,-,-		
	AH81-00614G	A/S-GEAR(A);-,PBT,AJ66-00004A,-,-,-,-		
	AH81-00614H	A/S-MOTOR-FEED;-,-,AJ31-00601E,-,-,-,-		
	AH81-00614J	A/S-MOTOR-PCB ASSY;-,-,AJ41-00601S,-,-,-		
	AH81-00614K	A/S-CONNECTOR;-,-,AJ37-00601A,-,-,-,-		
	AH92-01375A	**ASSY PCB-FRONT;MAX-WB630/650**		**COMMON**
UIC2	0904-001621	IC-I/O CONTROLLER;PT8300,16BIT,SOP,28P,3		
UIC3	0904-001621	IC-I/O CONTROLLER;PT8300,16BIT,SOP,28P,3		
UX2	2801-001394	CRYSTAL-UNIT;32.768KHz,20ppm,28-AAY,12.5		
UX1	2802-001174	RESONATOR-CERAMIC;10MHZ,0.5%,BK,8X3.5X3M		
UVR1	3406-001050	SWITCH-ROTARY;5V DC,0.5mA,click,12mm		
UVR2	3406-001050	SWITCH-ROTARY;5V DC,0.5mA,click,12mm		
UVR3	3406-001050	SWITCH-ROTARY;5V DC,0.5mA,click,12mm		
UCW5	3708-000451	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH		
UCW4	3708-000451	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH		
UCW2	3708-000451	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH		
UCW1	3708-000451	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH		
UCW3	3708-000454	CONNECTOR-FPC/FFC/PIC;22P,1.25mm,STRAIGH		
UCW6	3708-000454	CONNECTOR-FPC/FFC/PIC;22P,1.25mm,STRAIGH		
UCW7	3708-000454	CONNECTOR-FPC/FFC/PIC;22P,1.25mm,STRAIGH		
UCH1	3711-000827	CONNECTOR-HEADER;BOX,2P,1R,2mm,STRAIGHT,		
UCH2	3711-001018	CONNECTOR-HEADER;BOX,5P,1R,2mm,STRAIGHT,		
HJACK1	3722-000351	JACK-PHONE;11P,3.5PI,AG,BLK,-		
RE-EYE	AC59-60060A	MODULE REMOCON;GP1U281R,SHARP,38KHZ,-,-		
UVFD1	AH07-00066A	VF DISPLAY;HNA-16LM24T,MAX-B550/570/VB55		
UIC1	AH11-00074A	MASK ROM;LC876756A-5Z98,MAX-WB630/WB650		
UCA2	AH39-00101A	LEAD CONNECTOR ASSY;-,5295,51004,5P,150M		
UCA1	AH39-00109A	LEAD CONNECTOR ASSY;-,5295,51004,2P,140M		
	AH39-50001L	WIRE HARNESS;RING,1007#24,200MM,BLK		
	AH61-00521A	HOLDER-VFD;MAXL65,ABS,-,-,-,BLK,-		
MJACK1	3722-001190	JACK-PHONE;9P/2C,6.43PI,AU,BLK		OPTION
MJACK2	3722-001190	JACK-PHONE;9P/2C,6.43PI,AU,BLK		OPTION
UD5	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
UD18	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
UD17	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
UD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
MD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
UD22	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD23	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD27	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD30	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD21	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD20	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD19	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD16	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD15	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UZD1	0403-000393	DIODE-ZENER;UZP5.1B,5.1V,4.8-5.4V,1W,DO-		
UZD2	0403-000393	DIODE-ZENER;UZP5.1B,5.1V,4.8-5.4V,1W,DO-		
UQ2	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T		
UQ1	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T		
UQ6	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
UQ5	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
UQ4	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		

Location no	Code no.	Description	Specifiation	Remarks
UQ3	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
UQ9	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,		
UQ8	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,		
UQ7	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,		
UQ12	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-		
UQ11	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-		
ULD4	0601-001238	LED;ROUND,RED,3.1mm,697nm		
ULD3	0601-001238	LED;ROUND,RED,3.1mm,697nm		
ULD2	0601-001238	LED;ROUND,RED,3.1mm,697nm		
ULD1	0601-001238	LED;ROUND,RED,3.1mm,697nm		
UR62	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR69	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR106	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4		
UR107	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4		
UR90	2001-000221	R-CARBON;1.2Kohm,5%,1/8W,AA,TP,1.8x3.2m		
UR129	2001-000221	R-CARBON;1.2Kohm,5%,1/8W,AA,TP,1.8x3.2m		
UR130	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m		
UR91	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m		
UR112	2001-000258	R-CARBON;1.8Kohm,5%,1/8W,AA,TP,1.8x3.2m		
UR63	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR186	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR183	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR182	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR178	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR175	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR174	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR173	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR172	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR170	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR171	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR78	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR77	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR76	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR64	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR65	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR74	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR75	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR8	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR80	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR81	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR82	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR73	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR72	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR71	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR70	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR84	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR95	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR94	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR93	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR92	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR9	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR87	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR86	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR85	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR137	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR136	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR2	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR181	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR180	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR179	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR138	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR13	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR122	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR121	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR140	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR14	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR139	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR176	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR10	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR100	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR101	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR11	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR12	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR120	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR1	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR16	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR15	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR143	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR142	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR141	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
MR21	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR135	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR40	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR4	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR39	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR3	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR28	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR27	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR41	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR7	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR6	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR54	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR5	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR43	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		

Location no	Code no.	Description Specifiation	Remarks
UR42	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR26	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR25	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR24	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR23	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR21	2001-000295	R-CARBON;10MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR19	2001-000362	R-CARBON;150ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR133	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR131	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR111	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR109	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR108	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR89	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR128	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR22	2001-000435	R-CARBON;1Mohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR17	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR88	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR110	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR18	2001-000508	R-CARBON;220Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR124	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR44	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR145	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR52	2001-000613	R-CARBON;3.9Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR61	2001-000660	R-CARBON;33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR68	2001-000660	R-CARBON;33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR53	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR51	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR46	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR146	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR132	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR57	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR56	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR55	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
HR1	2001-000745	R-CARBON;4.7ohm,5%,1/8W,AA,TP,1.8x3.2mm	
HR2	2001-000745	R-CARBON;4.7ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR33	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR34	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR35	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR36	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR37	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR38	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR32	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
MR20	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR134	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR200	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR29	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR30	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR31	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR20	2001-000850	R-CARBON;560Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR119	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR113	2001-000995	R-CARBON;820ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR127	2001-000995	R-CARBON;820ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR58	2001-001192	R-CARBON(S);820ohm,5%,1/2W,AA,TP,2.4x6.4	
UR59	2001-001192	R-CARBON(S);820ohm,5%,1/2W,AA,TP,2.4x6.4	
UR60	2001-001192	R-CARBON(S);820ohm,5%,1/2W,AA,TP,2.4x6.4	
URV1	2103-000341	VR-SEMI;2Kohm,30%,1/10W,TOP	
UC11	2201-000300	C-CERAMIC,DISC;1nF,20%,50V,Y5T,TP,5x3,5	
HC2	2201-000300	C-CERAMIC,DISC;1nF,20%,50V,Y5T,TP,5x3,5	
HC1	2201-000300	C-CERAMIC,DISC;1nF,20%,50V,Y5T,TP,5x3,5	
UC8	2201-000389	C-CERAMIC,DISC;0.022nF,5%,50V,NP0,TP,5x3	
UC7	2201-000389	C-CERAMIC,DISC;0.022nF,5%,50V,NP0,TP,5x3	
ZC1	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m	
UC35	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m	
UC3	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m	
UC15	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m	
ZC2	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m	
ZC3	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m	
UC10	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m	
UC1	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m	
UC17	2201-000783	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,	
UC18	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
UC19	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
UC20	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
UC21	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
UC24	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
UC25	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
MC10	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7,5	
UC100	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7,5	
UC14	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7,5	
UC16	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7,5	
UC36	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7,5	
UC4	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7,5	
UC5	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7,5	
UC2	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm	
UC9	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm	
UC13	2401-001355	C-AL;470uF,20%,10V,GP,TP,8x11.5mm,5	
UC27	2401-001893	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
UC26	2401-001893	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
UC12	2401-001919	C-AL;2.2uF,20%,50V,-,TP,4x7mm,5	
UC6	2401-001931	C-AL;220nF,20%,50V,-,TP,4x7mm,5	
HL2	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
HL1	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm	
USW12	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	

Location no	Code no.	Description Specifiation	Remarks
USW13	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW14	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW11	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW10	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW1	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW4	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW3	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW2	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW16	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW15	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW9	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW8	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW7	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW6	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW5	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
PCB1	AH41-00448A	PCB-PCB FRONT;MAX-WB650/VB630/675,-,-,-,	
	AH92-01385A	**ASSY PCB-MAIN;MAX-WB630,**	**MAX-WB630**
RBD1	0402-001258	DIODE-BRIDGE;GBU606,600V,6A,SIP-4,BK	
RBD2	0402-001258	DIODE-BRIDGE;GBU606,600V,6A,SIP-4,BK	
OJACK	0603-001051	OPTIC TRANSMITTER;5V,6Mb/s,5m,-15dBm,660	
WIC1	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV	
WIC2	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV	
DIC1	1201-001819	IC-PREAMP;-,-,44P,-,-,-,PLASTIC,18V,625M	
RIC1	1203-001653	IC-VOLTAGE REGULATOR;4959,MULTIWATT,15P,	
FIC2	1204-001776	IC-SOUND PROCESSOR;TDA7442D,SOP,28P,295M	
RR9	2003-000455	R-METAL OXIDE(S);100ohm,5%,2W,AA,TP,4x12	
RR3	2003-000701	R-METAL OXIDE(S);470ohm,5%,2W,AA,TP,4x12	
RC18	2201-000546	C-CERAMIC,DISC;4.7nF,20%,400V,Y5U,BK,16x	
RC19	2201-000546	C-CERAMIC,DISC;4.7nF,20%,400V,Y5U,BK,16x	
RC14	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm	
RC5	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm	
RC2	2401-003381	C-AL;3300uF,20%,63V,GP,BK,22x40,10	
RC1	2401-003381	C-AL;3300uF,20%,63V,GP,BK,22x40,10	
RC4	2401-003755	C-AL;6800UF,20%,35V,BP,TP,22X40MM,1	
RC3	2401-003755	C-AL;6800UF,20%,35V,BP,TP,22X40MM,1	
OLPF	2901-001139	FILTER-EMI ON BOARD;50V,.5A,-,390PF,7X2.	
RF2	3601-000170	FUSE-CARTRIDGE;250V,1.6A,TIME-LAG,GLASS,	
RF1	3601-000263	FUSE-CARTRIDGE;250V,3.15A,TIME-LAG,GLASS	OPTION
RSW1	3408-000177	SWITCH-SLIDE;250V,5A,DPDT,<ON>-OFF-	OPTION
FCW4	3708-000181	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH	
FCW2	3708-000181	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH	
FCW1	3708-000181	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH	
TCW1	3708-001051	CONNECTOR-FPC/FFC/PIC;13P,1.25mm,ANGLE,S	
RCW2	3711-000190	CONNECTOR-HEADER;1WALL,2P,1R,7.92mm,STRA	
DCW2	3711-000907	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,	
CCW1	3711-001137	CONNECTOR-HEADER;BOX,8P,1R,2mm,STRAIGHT,	
RCW1	3711-001485	CONNECTOR-HEADER;NOWALL,3P,1R,8MM,STRAIG	
DCW3	3711-003107	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
DCW1	3711-003111	CONNECTOR-HEADER;BOX,6P,1R,2.5mm,STRAIGH	
RCW5	3711-003112	CONNECTOR-HEADER;BOX,8P,1R,2.5mm,STRAIGH	
ACW1	3711-003113	CONNECTOR-HEADER;BOX,9P,1R,2.5mm,STRAIGH	
AJCK	3722-000377	JACK-PIN;4P/2C,3.5mm,SN,BLK,#16~22	
	6003-000276	SCREW-TAPTITE;BH,+,B,M3,L10,ZPC(YEL),SWC	
	6003-000276	SCREW-TAPTITE;BH,+,B,M3,L10,ZPC(YEL),SWC	
OIC1	AH14-10004R	IC;M74HCU04,SOP,TAPE 14P	
DL1	AH26-10002W	TRANS TRAP-COIL;BIAS-TRAP105K,BIAS-TRAP,	
DL2	AH26-10002W	TRANS TRAP-COIL;BIAS-TRAP105K,BIAS-TRAP,	
DL4	AH26-10003C	TRANS TRAP-COIL;PCHNS-5371EQJ,BIAS-TRAP,	
RL2	AH27-10001F	COIL-CHOKE;27uH,K,Q30,-,-,DR(6.5*7.5),-,	
RL1	AH27-10001F	COIL-CHOKE;27uH,K,Q30,-,-,DR(6.5*7.5),-,	
RCW3	AH39-00045C	LEAD CONNECTOR ASSY;MAX-VL42,-,UL/CSA,HO	
	AH39-00052T	LEAD CONNECTOR ASSY;RXD-DV9,#2547,28,AWG	
	AH39-00085A	LEAD CONNECTOR ASSY;-,51004,5295,3P,150M	
OCW1	AH39-00096B	LEAD CONNECTOR ASSY;RXD-DV9,#1007,28,AWG	
	AH61-40014A	SUPPORT-RIVET;-,-,-,-,-,-,-	
	AH62-00044A	HEAT SINK-,IC;MAX-L85,AL 3.0T,-,-,-,-,-,	
	AH63-00278A	COVER-PCB;MAX-WL85,PVC 0.5T,-,-,-,-,CLR,	
WD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
TD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
TD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
FD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
RD2	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD12	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD1	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD11	0402-000151	DIODE-RECTIFIER;1N5392,100V,1.5A,DO-15,T	
RZD1	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,D	
WZD1	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,D	
FZD1	0403-000372	DIODE-ZENER;UZ9.1BM,9.1V,8.7-9.4V,500mW,	
RZD5	0403-000379	DIODE-ZENER;UZP12B,12V,11.4-12.6V,1W,DO-	
RZD3	0403-000570	DIODE-ZENER;UZP18B,18V,16.9-19.1V,1W,DO-	
RZD2	0403-000570	DIODE-ZENER;UZP18B,18V,16.9-19.1V,1W,DO-	
RZD4	0403-001010	DIODE-ZENER;UZ5.6BCC,5.6V,5.64-5.88V,500	
DQ9	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
DQ8	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
DQ7	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
DQ6	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
RQ2	0501-000294	TR-SMALL SIGNAL;KSA708-Y,PNP,800mW,TO-92	
CQ2	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-9	
CQ3	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-9	
DQ4	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
FQ1	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
DQ2	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	

Location no	Code no.	Description Specifiation	Remarks
DQ10	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
DQ1	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
DQ5	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9	
RQ1	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,	
DQ3	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,	
CQ1	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-	
DR8	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR1	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR8	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
CR4	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
CR7	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR26	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR6	2001-000012	R-CARBON;680Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR8	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
RR14	2001-000017	R-CARBON;4.7ohm,5%,1/4W,AA,TP,2.4x6.4mm	
FR11	2001-000027	R-CARBON;100ohm,5%,1/4W,AA,TP,2.4x6.4mm	
RR10	2001-000038	R-CARBON;390ohm,5%,1/4W,AA,TP,2.4x6.4mm	
WR50	2001-000109	R-CARBON(S);470ohm,5%,1/2W,AA,TP,2.4x6.4	
RR13	2001-000111	R-CARBON;150ohm,5%,1/4W,AA,TP,2.4x6.4mm	
WR7	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m	
TR3	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR4	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR5	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR6	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR1	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR2	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR1	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR17	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR2	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR4	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR1	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR9	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR3	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR24	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR12	2001-000331	R-CARBON;12Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR9	2001-000331	R-CARBON;12Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR18	2001-000362	R-CARBON;150ohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR4	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR10	2001-000435	R-CARBON;1Mohm,5%,1/8W,AA,TP,1.8x3.2mm	
KR15	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
KR12	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR17	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR16	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR6	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR13	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR23	2001-000456	R-CARBON;2.2ohm,5%,1/4W,AA,TP,2.4x6.4mm	
RR11	2001-000472	R-CARBON;2.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
WR3	2001-000515	R-CARBON;220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR10	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR9	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR5	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR12	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR25	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR27	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR8	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR12	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR7	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR14	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR21	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR20	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
CR1	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
WR5	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR7	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR5	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR28	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR2	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR4	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR6	2001-000613	R-CARBON;3.9Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR16	2001-000613	R-CARBON;3.9Kohm,5%,1/8W,AA,TP,1.8x3.2m	
CR5	2001-000613	R-CARBON;3.9Kohm,5%,1/8W,AA,TP,1.8x3.2m	
CR2	2001-000613	R-CARBON;3.9Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR13	2001-000645	R-CARBON;330Kohm,5%,1/8W,AA,TP,1.8x3.2m	
WR8	2001-000660	R-CARBON;33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR4	2001-000702	R-CARBON;39Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR12	2001-000702	R-CARBON;39Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR29	2001-000702	R-CARBON;39Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR10	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
TR11	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
TR7	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
WR11	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR11	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
KR6	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
KR9	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR5	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR23	2001-000773	R-CARBON;470Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR3	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR6	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR20	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR12	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR13	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR2	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
CR3	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
CR6	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	

Location no	Code no.	Description Specifiation	Remarks
DR17	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR19	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR14	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR15	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR30	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR9	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR10	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR21	2001-000869	R-CARBON;56ohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR20	2001-000869	R-CARBON;56ohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR7	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR37	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR36	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR35	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR15	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR22	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR34	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR33	2001-000924	R-CARBON;680ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR32	2001-000924	R-CARBON;680ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR31	2001-000924	R-CARBON;680ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR30	2001-000924	R-CARBON;680ohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR2	2001-001153	R-CARBON(S);47ohm,5%,1/2W,AA,TP,2.4x6.4m	
RR18	2001-001153	R-CARBON(S);47ohm,5%,1/2W,AA,TP,2.4x6.4m	
RR1	2001-001153	R-CARBON(S);47ohm,5%,1/2W,AA,TP,2.4x6.4m	
DSR1	2103-000248	VR-SEMI;200Kohm,30%,1/10W,TOP	
DSR2	2103-000248	VR-SEMI;200Kohm,30%,1/10W,TOP	
RC26	2201-000161	C-CERAMIC,DISC;10nF,+80-20%,500V,Y5V,TP,	
RC25	2201-000161	C-CERAMIC,DISC;10nF,+80-20%,500V,Y5V,TP,	
FC28	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
FC29	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
FC3	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
FC6	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
FC27	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
FC26	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
DC33	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
DC17	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
OC3	2201-000381	C-CERAMIC,DISC;22nF,+80%,50V,-,,8x4mm,-	
OC1	2201-000487	C-CERAMIC,DISC;33pF,5%,50V,SL,TP,5x3,5m	
WC4	2201-000557	C-CERAMIC,DISC;0.47nF,10%,50V,SL,TP,8x3.	
DC29	2201-000674	C-CERAMIC,DISC;0.82nF,10%,50V,Y5P,BK,5x3	
DC1	2201-000674	C-CERAMIC,DISC;0.82nF,10%,50V,Y5P,BK,5x3	
TC5	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
TC4	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
TC3	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
TC2	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
TC1	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
DC3	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
TC6	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
TC7	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
FC14	2301-000361	C-FILM,PEF;1.2nF,10%,50V,TP,-,5mm	
DC23	2301-000361	C-FILM,PEF;1.2nF,10%,50V,TP,-,5mm	
DC22	2301-000361	C-FILM,PEF;1.2nF,10%,50V,TP,-,5mm	
DC19	2301-000361	C-FILM,PEF;1.2nF,10%,50V,TP,-,5mm	
DC18	2301-000361	C-FILM,PEF;1.2nF,10%,50V,TP,-,5mm	
FC17	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
FC16	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
FC15	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
FC32	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
FC7	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
WC5	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
DC10	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
DC25	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
DC26	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
FC13	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
FC1	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
DC7	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
DC11	2301-000379	C-FILM,PEF;10nF,10%,50V,TP,6x12x3.5mm,-	
DC24	2301-000379	C-FILM,PEF;10nF,10%,50V,TP,6x12x3.5mm,-	
WC7	2301-000387	C-FILM,PEF;150nF,10%,50V,TP,12.5x15x7.5,	
DC14	2301-000404	C-FILM,PEF;2.2nF,10%,50V,TP,5.5x12x3mm,-	
DC15	2301-000404	C-FILM,PEF;2.2nF,10%,50V,TP,5.5x12x3mm,-	
DC16	2301-000404	C-FILM,PEF;2.2nF,10%,50V,TP,5.5x12x3mm,-	
DC13	2301-000407	C-FILM,PEF;2.7nF,10%,50V,TP,5.5x12x3mm,-	
WC9	2301-000412	C-FILM,PEF;22nF,10%,50V,TP,8x12x4mm,-	
CC2	2301-000449	C-FILM,PEF;47nF,10%,50V,TP,9.5x12.5x5mm,	
FC11	2301-000454	C-FILM,PEF;5.6nF,10%,50V,TP,6x12x3,3.5mm	
FC12	2301-000454	C-FILM,PEF;5.6nF,10%,50V,TP,6x12x3,3.5mm	
CC3	2401-000129	C-AL;1000uF,20%,16V,GP,-,10x16mm,5	
OC2	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
RC6	2401-000357	C-AL;100uF,20%,50V,GP,-,8x11.5,3.5m	
CC5	2401-000419	C-AL;10UF,20%,16V,GP,5*11,5MM,TP	
DC30	2401-000419	C-AL;10UF,20%,16V,GP,5*11,5MM,TP	
RC9	2401-000438	C-AL;10uF,20%,25V,GP,-,5x11,2mm	
WC8	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm	
WC3	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm	
WC2	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm	
WC1	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm	
FC20	2401-000649	C-AL;2.2uF,20%,50V,BP,TP,5x11,5	
FC21	2401-000649	C-AL;2.2uF,20%,50V,BP,TP,5x11,5	
DC2	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
RC11	2401-000795	C-AL;220uF,20%,16V,GP,TP,8x12mm,5mm	
RC10	2401-000907	C-AL;22uF,20%,16V,GP,TP,5x11mm,5mm	
DC5	2401-001080	C-AL;330nF,20%,50V,GP,-,5x11,2mm	
DC4	2401-001102	C-AL;330uF,20%,16V,GP,TP,8x11.5mm,5	

Location no	Code no.	Description	Specifiation	Remarks
RC8	2401-001625	C-AL;6.8uF,20%,50V,GP,TP,5x11,5		
FC5	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5		
CC4	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5		
FC31	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP		
FC8	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP		
FC9	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP		
RC7	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP		
DC20	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP		
FC22	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP		
FC23	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP		
FC30	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP		
FC4	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm		
FC33	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm		
FC25	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm		
FC2	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm		
CC1	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm		
FC24	2401-001965	C-AL;470nF,20%,50V,BP,TP,4x7mm,5mm		
DC32	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm		
DC31	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm		
DC21	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm		
DC12	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm		
DC9	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm		
FC10	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm		
FC18	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm		
FC19	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm		
DC27	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm		
DC28	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm		
DC6	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm		
DC8	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm		
CL1	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm		
CL1	2701-000116	INDUCTOR-AXIAL;10uH,10%,4.2x9.8mm		
CL2	2701-000179	INDUCTOR-AXIAL;33uH,10%,4.2x9.8mm		
DL3	2701-000298	INDUCTOR-AXIAL;470uH,10%,4.2x9.8mm		
RF2	3602-000147	FUSE-CLIP;250V,7.5A,30mohm		
PCB	AH41-00434A	PCB;MAX-B550/570/VB555/D,-,-,-,-,3		
	AH92-01387A	**ASSY PCB-AMP;MAX-WB630**		**MAX-WB630**
PIC1	1201-001582	IC-POWER AMP;402-070,SIP,15P,-,DUAL,30dB		
PIC2	1201-001856	IC-POWER AMP;STK442-090,SIP,14P,233MIL,S		
PR42	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x		
PR41	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x		
PR34	2003-000390	R-METAL OXIDE(S);0.27OHM,5%,2W,AA,TP,		
PR33	2003-000390	R-METAL OXIDE(S);0.27OHM,5%,2W,AA,TP,		
PR32	2003-000390	R-METAL OXIDE(S);0.27OHM,5%,2W,AA,TP,		
PR31	2003-000390	R-METAL OXIDE(S);0.27OHM,5%,2W,AA,TP,		
PR6	2003-000578	R-METAL OXIDE(S);220ohm,5%,2W,AA,TP,4x12		
PR5	2003-000578	R-METAL OXIDE(S);220ohm,5%,2W,AA,TP,4x12		
PR45	2009-001117	R-METAL PLATE;0.1OHM,5%,5W,CL,BK,5X13X18		
PR46	2009-001117	R-METAL PLATE;0.1OHM,5%,5W,CL,BK,5X13X18		
PR47	2009-001117	R-METAL PLATE;0.1OHM,5%,5W,CL,BK,5X13X18		
PR59	2009-001117	R-METAL PLATE;0.1OHM,5%,5W,CL,BK,5X13X18		
PR58	2009-001117	R-METAL PLATE;0.1OHM,5%,5W,CL,BK,5X13X18		
PR48	2009-001117	R-METAL PLATE;0.1OHM,5%,5W,CL,BK,5X13X18		
PC25	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
PC24	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
PC23	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
PC22	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
JVR1	3406-001054	SWITCH-ROTARY;5V DC,0.5mA,-,7.5mm		
PREL2	3501-001197	RELAY-MINIATURE;12VDC,0.54W,44.4mA,1Form		
PREL1	3501-001197	RELAY-MINIATURE;12VDC,0.54W,44.4mA,1Form		
PW4	3708-000181	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH		
JCW1	3708-000451	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH		
PW1	3710-001793	CONNECTOR-SOCKET;9P,1R,2.5MM,STRAIGHT,SN		
PW2	3710-001793	CONNECTOR-SOCKET;9P,1R,2.5MM,STRAIGHT,SN		
PCW1	3711-004989	CONNECTOR-HEADER;2WALL,9P,1R,2.5MM,ANGLE		
PCW2	3711-004989	CONNECTOR-HEADER;2WALL,9P,1R,2.5MM,ANGLE		
SPJACK	3716-001164	TERMINAL-BLOCK;SOLDER,8P,-,60V,7A		
	6003-001230	SCREW-TAPTITE;BH,+,B,M3,L16,ZPC(YEL),SWR		
PL5	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
PL6	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
PL7	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
PL8	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
PL4	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
PL3	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
PL2	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
PL1	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
PCW3	AH39-00295A	W/HARNESS UNIT;MAX-L85,-,-,9P,-,-,-,SCN-		
	AH60-10051A	SCREW-TAPTITE;-,-,FE,-,B,M3,L8,-,-,-		
	AH61-00973A	BRACKET-H/SINK,L;MAX-WB650,SECC T1.0,-,-		
	AH61-00977A	BRACKET-H/SINK,R;NAX-WB650,SECC T1.0,-,-		
	AH62-00063D	HEAT SINK-,M;MAX-B570,AL EXTR,-,-,-,-,-,		
PD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
PD5	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
PD3	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
PD2	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
PD1	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
PZD1	0403-000382	DIODE-ZENER;UZP15B,15V,13.9-15.6V,1W,DO-		
PZD2	0403-000382	DIODE-ZENER;UZP15B,15V,13.9-15.6V,1W,DO-		
PQ9	0501-000296	TR-SMALL SIGNAL;KSA709-Y,PNP,800mW,TO-92		
PQ6	0501-000296	TR-SMALL SIGNAL;KSA709-Y,PNP,800mW,TO-92		
PQ10	0501-000296	TR-SMALL SIGNAL;KSA709-Y,PNP,800mW,TO-92		
PQ8	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-9		
PQ5	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-9		

Location no	Code no.	Description	Specifiation	Remarks
PQ16	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-		
PQ17	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-		
PQ4	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
PQ3	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
PQ2	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
PQ15	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
PQ1	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
PQ11	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
PQ12	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
PQ14	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
PQ7	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-		
PQ13	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-		
JLD5	0601-001238	LED;ROUND,RED,3.1mm,697nm		
JLD6	0601-001238	LED;ROUND,RED,3.1mm,697nm		
JLD7	0601-001238	LED;ROUND,RED,3.1mm,697nm		
JLD8	0601-001238	LED;ROUND,RED,3.1mm,697nm		
JLD9	0601-001238	LED;ROUND,RED,3.1mm,697nm		
JLD1	0601-001238	LED;ROUND,RED,3.1mm,697nm		
JLD10	0601-001238	LED;ROUND,RED,3.1mm,697nm		
JLD2	0601-001238	LED;ROUND,RED,3.1mm,697nm		
JLD3	0601-001238	LED;ROUND,RED,3.1mm,697nm		
JLD4	0601-001238	LED;ROUND,RED,3.1mm,697nm		
PR69	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR65	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR68	2001-000019	R-CARBON(S);10ohm,5%,1/2W,AA,TP,2.4x6.4m		
PR64	2001-000019	R-CARBON(S);10ohm,5%,1/2W,AA,TP,2.4x6.4m		
JR17	2001-000221	R-CARBON;1.2Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR36	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR30	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR28	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m		
JR1	2001-000258	R-CARBON;1.8Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR70	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR72	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR87	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR57	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR13	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR20	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR56	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR79	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR78	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR76	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
JR7	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
JR15	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
JR20	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
JR21	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
JR4	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
JR6	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
1R5	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
JR11	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
JR12	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
JR13	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
JR14	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
PR51	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR81	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR82	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR84	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR85	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR50	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
JR18	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR15	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR18	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR19	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR24	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
JR2	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR77	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR74	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR67	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR63	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR4	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
JR9	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR66	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR62	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
JR3	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR23	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR71	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR73	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR80	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR83	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
JR22	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
JR50	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR16	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR17	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR22	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR61	2001-000780	R-CARBON;470ohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR60	2001-000780	R-CARBON;470ohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR21	2001-000780	R-CARBON;470ohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR14	2001-000780	R-CARBON;470ohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR75	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR86	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR3	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR49	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR52	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR54	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		

Location no	Code no.	Description	Specifiation	Remarks
PR55	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
JR10	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR27	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR29	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR35	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR40	2001-000869	R-CARBON;56ohm,5%,1/8W,AA,TP,1.8x3.2mm		
JR8	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m		
JR16	2001-000995	R-CARBON;820ohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR12	2001-001000	R-CARBON;82Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR11	2001-001000	R-CARBON;82Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR25	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x		
PR26	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x		
PR44	2003-000428	R-METAL OXIDE(S);1.5Kohm,5%,1W,AA,TP,3.3		
PR43	2003-000428	R-METAL OXIDE(S);1.5Kohm,5%,1W,AA,TP,3.3		
PR9	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x		
PR8	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x		
PR7	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x		
PR38	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x		
PR10	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x		
PC13	2201-000300	C-CERAMIC,DISC;1nF,20%,50V,Y5T,TP,5x3,5		
PC12	2201-000300	C-CERAMIC,DISC;1nF,20%,50V,Y5T,TP,5x3,5		
PC28	2201-000338	C-CERAMIC,DISC;2.2nF,20%,50V,Y5T,TP,5.0x		
PC29	2201-000338	C-CERAMIC,DISC;2.2nF,20%,50V,Y5T,TP,5.0x		
PC15	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3		
PC11	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3		
PC55	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x		
PC56	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x		
PC57	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x		
PC58	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x		
PC54	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x		
PC53	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x		
PC52	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x		
PC51	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x		
PC62	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m		
PC61	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m		
PC60	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m		
PC59	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m		
PC27	2201-000674	C-CERAMIC,DISC;0.82nF,10%,50V,Y5P,BK,5x3		
PC26	2201-000674	C-CERAMIC,DISC;0.82nF,10%,50V,Y5P,BK,5x3		
PC3	2201-000783	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,		
PC8	2201-000783	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,		
PC5	2201-000783	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,		
PC4	2201-000783	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,		
PC35	2201-000838	C-CERAMIC,DISC;3pF,0.3pF,50V,CH,TP,5x3.5		
PC33	2201-000838	C-CERAMIC,DISC;3pF,0.3pF,50V,CH,TP,5x3.5		
PC14	2201-000838	C-CERAMIC,DISC;3pF,0.3pF,50V,CH,TP,5x3.5		
PC10	2201-000838	C-CERAMIC,DISC;3pF,0.3pF,50V,CH,TP,5x3.5		
PC38	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		
PC34	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		
JC2	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3		
JC1	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3		
PC7	2301-000379	C-FILM,PEF;10nF,10%,50V,TP,6x12x3.5mm,-		
PC16	2301-000379	C-FILM,PEF;10nF,10%,50V,TP,6x12x3.5mm,-		
PC9	2401-000357	C-AL;100uF,20%,50V,GP,-,8x11.5,3.5m		
PC50	2401-000357	C-AL;100uF,20%,50V,GP,-,8x11.5,3.5m		
PC21	2401-000357	C-AL;100uF,20%,50V,GP,-,8x11.5,3.5m		
PC20	2401-000357	C-AL;100uF,20%,50V,GP,-,8x11.5,3.5m		
PC18	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm		
PC19	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm		
PC61	2401-000970	C-AL;22uF,20%,50V,WT,TP,5x11,5		
PC60	2401-001538	C-AL;47uF,20%,25V,GP,TP,5x11mm,5mm		
PC37	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5		
PC36	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5		
PC1	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5		
PC8	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm		
PC17	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm		
PC32	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm		
PC31	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm		
JSW4	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
JSW5	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
JSW6	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
JSW7	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
JSW8	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
JSW9	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
JSW3	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
JSW1	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
JSW10	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
JSW11	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
JSW2	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
JSW13	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
JSW12	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
PCB	AH41-00449A	PCB-PCB AMP;MAX-WB650/VB630/675,-,-,-,1.		
	AH92-01373A	**ASSY PCB-MAIN;MAX-WB650,**		**MAX-WB650**
RBD1	0402-001258	DIODE-BRIDGE;GBU606,600V,6A,SIP-4,BK		
RBD2	0402-001258	DIODE-BRIDGE;GBU606,600V,6A,SIP-4,BK		
OJACK	0603-001051	OPTIC TRANSMITTER;5V,6Mb/s,5m,-15dBm,660		
WIC2	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV		
WIC1	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV		
DIC1	1201-001819	IC-PREAMP;-,-,44P,-,-,-,PLASTIC,18V,625M		
RIC1	1203-001653	IC-VOLTAGE REGULATOR;4959,MULTIWATT,15P,		
FIC2	1204-001776	IC-SOUND PROCESSOR;TDA7442D,SOP,28P,295M		
RR9	2003-000455	R-METAL OXIDE(S);100ohm,5%,2W,AA,TP,4x12		

Location no	Code no.	Description	Specifiation	Remarks
RR3	2003-000701	R-METAL OXIDE(S);470ohm,5%,2W,AA,TP,4x12		
RC18	2201-000546	C-CERAMIC,DISC;4.7nF,20%,400V,Y5U,BK,16x		
RC19	2201-000546	C-CERAMIC,DISC;4.7nF,20%,400V,Y5U,BK,16x		
RC5	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
RC2	2401-003381	C-AL;3300uF,20%,63V,GP,BK,22x40,10		
RC1	2401-003381	C-AL;3300uF,20%,63V,GP,BK,22x40,10		
RC4	2401-003755	C-AL;6800UF,20%,35V,BP,TP,22X40MM,1		
RC3	2401-003755	C-AL;6800UF,20%,35V,BP,TP,22X40MM,1		
OLPF	2901-001139	FILTER-EMI ON BOARD;50V,.5A,-,390PF,7X2.		
RF1	3601-000248	FUSE-CARTRIDGE;250V,2A,TIME-LAG,GLASS,5x		
FCW4	3708-000181	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH		
FCW2	3708-000181	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH		
FCW1	3708-000181	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH		
TCW1	3708-001051	CONNECTOR-FPC/FFC/PIC;13P,1.25mm,ANGLE,S		
RCW2	3711-000190	CONNECTOR-HEADER;1WALL,2P,1R,7.92mm,STRA		
DCW2	3711-000907	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,		
CCW1	3711-001137	CONNECTOR-HEADER;BOX,8P,1R,2mm,STRAIGHT,		
RCW1	3711-001485	CONNECTOR-HEADER;NOWALL,3P,1R,8MM,STRAIG		
DCW3	3711-003107	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH		
DCW1	3711-003111	CONNECTOR-HEADER;BOX,6P,1R,2.5mm,STRAIGH		
RCW5	3711-003112	CONNECTOR-HEADER;BOX,8P,1R,2.5mm,STRAIGH		
ACW1	3711-003113	CONNECTOR-HEADER;BOX,9P,1R,2.5mm,STRAIGH		
AJCK	3722-000377	JACK-PIN;4P/2C,3.5mm,SN,BLK,#16~22		
	6003-000276	SCREW-TAPTITE;BH,+,B,M3,L10,ZPC(YEL),SWC		
	6003-000276	SCREW-TAPTITE;BH,+,B,M3,L10,ZPC(YEL),SWC		
OIC1	AH14-10004R	IC;M74HCU04,SOP,TAPE 14P		
DL1	AH26-10002W	TRANS TRAP-COIL;BIAS-TRAP105K,BIAS-TRAP,		
DL2	AH26-10002W	TRANS TRAP-COIL;BIAS-TRAP105K,BIAS-TRAP,		
DL4	AH26-10003C	TRANS TRAP-COIL;PCHNS-5371EQJ,BIAS-TRAP,		
RL1	AH27-10001F	COIL-CHOKE;27uH,K,Q30,-,-,DR(6.5*7.5),-,		
RL3	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
RL2	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
OCW1	AH39-00096B	LEAD CONNECTOR ASSY;RXD-DV9,#1007,28,AWG		
	AH61-40014A	SUPPORT-RIVET;-,-,-,-,-,-,-		
	AH62-00044A	HEAT SINK-,IC;MAX-L85,AL 3.0T,-,-,-,-,-		
	AH63-00278A	COVER-PCB;MAX-WL85,PVC 0.5T,-,-,-,-,CLR,		
FD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
TD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
TD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
WD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
RD1	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
RD12	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
RD2	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
RD13	0402-000151	DIODE-RECTIFIER;1N5392,100V,1.5A,DO-15,T		
RD9	0402-000151	DIODE-RECTIFIER;1N5392,100V,1.5A,DO-15,T		
RD10	0402-000151	DIODE-RECTIFIER;1N5392,100V,1.5A,DO-15,T		
RD11	0402-000151	DIODE-RECTIFIER;1N5392,100V,1.5A,DO-15,T		
RZD1	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,D		
WZD1	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,D		
FZD1	0403-000372	DIODE-ZENER;UZ9.1BM,9.1V,8.7-9.4V,500mW,		
RZD5	0403-000379	DIODE-ZENER;UZP12B,12V,11.4-12.6V,1W,DO-		
RZD3	0403-000570	DIODE-ZENER;UZP18B,18V,16.9-19.1V,1W,DO-		
RZD2	0403-000570	DIODE-ZENER;UZP18B,18V,16.9-19.1V,1W,DO-		
RZD4	0403-001010	DIODE-ZENER;UZ5.6BCC,5.6V,5.64-5.88V,500		
DQ8	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,		
DQ7	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,		
DQ6	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,		
DQ9	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,		
RQ2	0501-000294	TR-SMALL SIGNAL;KSA708-Y,PNP,800mW,TO-92		
CQ2	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-9		
CQ3	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-9		
DQ4	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-		
DQ1	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T		
FQ1	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T		
DQ10	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
DQ10	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
DQ11	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
DQ5	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
RQ1	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,		
DQ3	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,		
DQ40	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-		
CQ1	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-		
FR1	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
CR7	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
CR5	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
CR4	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
CR2	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
FR8	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
WR6	2001-000012	R-CARBON;680Kohm,5%,1/8W,AA,TP,1.8x3.2m		
RR8	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM		
RR14	2001-000017	R-CARBON;4.7ohm,5%,1/4W,AA,TP,2.4x6.4mm		
FR11	2001-000027	R-CARBON;100ohm,5%,1/4W,AA,TP,2.4x6.4mm		
RR10	2001-000038	R-CARBON;390ohm,5%,1/4W,AA,TP,2.4x6.4mm		
DR18	2001-000111	R-CARBON;150ohm,5%,1/4W,AA,TP,2.4x6.4mm		
WR7	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m		
DR4	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
DR2	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
DR17	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
DR1	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
WR1	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
TR6	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
TR5	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
TR4	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		

Location no	Code no.	Description Specifiation	Remarks
TR3	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR2	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR1	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR24	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR3	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR9	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR9	2001-000302	R-CARBON;10ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR11	2001-000302	R-CARBON;10ohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR12	2001-000331	R-CARBON;12Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR9	2001-000331	R-CARBON;12Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR4	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
KR30	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR10	2001-000435	R-CARBON;1Mohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR17	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
KR12	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
KR15	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR16	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR6	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR13	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR11	2001-000472	R-CARBON;2.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
WR3	2001-000515	R-CARBON;220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR10	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR5	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR8	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR12	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR7	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR14	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR4	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR5	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR7	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
WR5	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR2	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR28	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR21	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR20	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
CR1	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR6	2001-000613	R-CARBON;3.9Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR13	2001-000645	R-CARBON;330Kohm,5%,1/8W,AA,TP,1.8x3.2m	
WR8	2001-000660	R-CARBON;33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR29	2001-000702	R-CARBON;39Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR12	2001-000702	R-CARBON;39Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR4	2001-000702	R-CARBON;39Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR5	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
KR9	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
KR6	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR25	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR22	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR16	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR15	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
TR10	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
TR11	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
TR7	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
WR11	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR23	2001-000773	R-CARBON;470Kohm,5%,1/8W,AA,TP,1.8x3.2m	
WR50	2001-000780	R-CARBON;470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR3	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR6	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR20	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR12	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR15	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR14	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR19	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR17	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
CR3	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
CR6	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR2	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR13	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR10	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR9	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
WR20	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR20	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR21	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR27	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR7	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR37	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR36	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR35	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR34	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR12	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR33	2001-000924	R-CARBON;680ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR32	2001-000924	R-CARBON;680ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR31	2001-000924	R-CARBON;680ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR30	2001-000924	R-CARBON;680ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR8	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8x3.2m	
DR26	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8x3.2m	
RR13	2001-001004	R-CARBON;82ohm,5%,1/4W,AA,TP,2.4x6.4mm	
DR23	2001-001093	R-CARBON(S);2.2Kohm,5%,1/2W,AA,TP,2.4x6.	
RR1	2001-001153	R-CARBON(S);47ohm,5%,1/2W,AA,TP,2.4x6.4m	
RR2	2001-001153	R-CARBON(S);47ohm,5%,1/2W,AA,TP,2.4x6.4m	
DSR1	2103-000248	VR-SEMI;200Kohm,30%,1/10W,TOP	
DSR2	2103-000248	VR-SEMI;200Kohm,30%,1/10W,TOP	
RC26	2201-000161	C-CERAMIC,DISC;10nF,+80-20%,500V,Y5V,TP,	
RC25	2201-000161	C-CERAMIC,DISC;10nF,+80-20%,500V,Y5V,TP,	

Location no	Code no.	Description Specifiation	Remarks
DC23	2201-000163	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,TP,7	
DC22	2201-000163	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,TP,7	
DC19	2201-000163	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,TP,7	
DC18	2201-000163	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,TP,7	
FC29	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
FC3	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
FC6	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
FC28	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
FC27	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
FC26	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
DC17	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
OC3	2201-000381	C-CERAMIC,DISC;22nF,+80%,50V,-,,8x4mm,-	
OC1	2201-000487	C-CERAMIC,DISC;33pF,5%,50V,SL,TP,5x3,5m	
WC4	2201-000557	C-CERAMIC,DISC;0.47nF,10%,50V,SL,TP,8x3.	
DC1	2201-000674	C-CERAMIC,DISC;0.82nF,10%,50V,Y5P,BK,5x3	
DC29	2201-000674	C-CERAMIC,DISC;0.82nF,10%,50V,Y5P,BK,5x3	
TC7	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
TC6	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
TC5	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
FC14	2301-000361	C-FILM,PEF;1.2nF,10%,50V,TP,-,5mm	
FC15	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
FC16	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
FC17	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
FC32	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
WC5	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
DC10	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
DC25	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
DC26	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
DC7	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
FC13	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
DC24	2301-000379	C-FILM,PEF;10nF,10%,50V,TP,6x12x3.5mm,-	
DC11	2301-000379	C-FILM,PEF;10nF,10%,50V,TP,6x12x3.5mm,-	
DC16	2301-000404	C-FILM,PEF;2.2nF,10%,50V,TP,5.5x12x3mm,-	
DC15	2301-000404	C-FILM,PEF;2.2nF,10%,50V,TP,5.5x12x3mm,-	
DC14	2301-000404	C-FILM,PEF;2.2nF,10%,50V,TP,5.5x12x3mm,-	
DC13	2301-000407	C-FILM,PEF;2.7nF,10%,50V,TP,5.5x12x3mm,-	
WC9	2301-000412	C-FILM,PEF;22nF,10%,50V,TP,8x12x4mm,-	
DC31	2301-000412	C-FILM,PEF;22nF,10%,50V,TP,8x12x4mm,-	
CC2	2301-000449	C-FILM,PEF;47nF,10%,50V,TP,9.5x12.5x5mm,	
FC12	2301-000454	C-FILM,PEF;5.6nF,10%,50V,TP,6x12x3,3.5mm	
FC11	2301-000454	C-FILM,PEF;5.6nF,10%,50V,TP,6x12x3,3.5mm	
CC3	2401-000129	C-AL;1000uF,20%,16V,GP,-,10x16mm,5	
OC2	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
RC6	2401-000357	C-AL;100uF,20%,50V,GP,-,8x11.5,3.5m	
CC5	2401-000419	C-AL;10UF,20%,16V,GP,5*11,5MM,TP	
DC30	2401-000419	C-AL;10UF,20%,16V,GP,5*11,5MM,TP	
RC9	2401-000438	C-AL;10uF,20%,25V,GP,-,5x11,2mm	
WC1	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm	
WC2	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm	
WC3	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm	
WC8	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm	
FC20	2401-000649	C-AL;2.2uF,20%,50V,BP,TP,5x11,5	
FC21	2401-000649	C-AL;2.2uF,20%,50V,BP,TP,5x11,5	
DC2	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
RC11	2401-000795	C-AL;220uF,20%,16V,GP,TP,8x12mm,5mm	
CC1	2401-000907	C-AL;22uF,20%,16V,GP,TP,5x11mm,5mm	
FC10	2401-000907	C-AL;22uF,20%,16V,GP,TP,5x11mm,5mm	
RC10	2401-000907	C-AL;22uF,20%,16V,GP,TP,5x11mm,5mm	
FC1	2401-001022	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
DC5	2401-001080	C-AL;330nF,20%,50V,GP,-,5x11,2mm	
DC4	2401-001102	C-AL;330uF,20%,16V,GP,TP,8x11.5mm,5	
RC8	2401-001625	C-AL;6.8uF,20%,50V,GP,TP,5x11,5	
CC4	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5	
RC7	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP	
FC9	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP	
FC8	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP	
FC23	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP	
FC22	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP	
DC20	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP	
FC25	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm	
FC2	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm	
FC33	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm	
FC4	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm	
FC24	2401-001965	C-AL;470nF,20%,50V,BP,TP,4x7mm,5mm	
DC32	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm	
DC21	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm	
DC12	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm	
FC19	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
FC18	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
DC9	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
DC8	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
DC6	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
DC28	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
DC27	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
CL1	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
CL1	2701-000116	INDUCTOR-AXIAL;10uH,10%,4.2x9.8mm	
CL2	2701-000179	INDUCTOR-AXIAL;33uH,10%,4.2x9.8mm	
DL3	2701-000298	INDUCTOR-AXIAL;470uH,10%,4.2x9.8mm	
RF2	3602-000147	FUSE-CLIP;250V,7.5A,30mohm	
PCB	AH41-00434A	PCB;MAX-B550/570/VB555/D,-,-,-,-,3	
	AH92-01374A	**ASSY PCB-AMP;MAX-WB650,**	**MAX-WB650**
PIC1	1201-001582	IC-POWER AMP;402-070,SIP,15P,-,DUAL,30dB	

Location no	Code no.	Description	Specifiation	Remarks
PIC2	1201-001844	IC-POWER AMP;STK412-020,SIP,18P,2520MIL,		
PR41	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x		
PR42	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x		
PR31	2003-000390	R-METAL OXIDE(S);0.27OHM,5%,2W,AA,TP,		
PR34	2003-000390	R-METAL OXIDE(S);0.27OHM,5%,2W,AA,TP,		
PR33	2003-000390	R-METAL OXIDE(S);0.27OHM,5%,2W,AA,TP,		
PR32	2003-000390	R-METAL OXIDE(S);0.27OHM,5%,2W,AA,TP,		
PR5	2003-000578	R-METAL OXIDE(S);220ohm,5%,2W,AA,TP,4x12		
PR6	2003-000578	R-METAL OXIDE(S);220ohm,5%,2W,AA,TP,4x12		
PR45	2009-001117	R-METAL PLATE;0.1OHM,5%,5W,CL,BK,5X13X18		
PR46	2009-001117	R-METAL PLATE;0.1OHM,5%,5W,CL,BK,5X13X18		
PR47	2009-001117	R-METAL PLATE;0.1OHM,5%,5W,CL,BK,5X13X18		
PR48	2009-001117	R-METAL PLATE;0.1OHM,5%,5W,CL,BK,5X13X18		
PR58	2009-001117	R-METAL PLATE;0.1OHM,5%,5W,CL,BK,5X13X18		
PR59	2009-001117	R-METAL PLATE;0.1OHM,5%,5W,CL,BK,5X13X18		
PC22	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
PC23	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
PC24	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
PC25	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
JVR1	3406-001054	SWITCH-ROTARY;5V DC,0.5mA,-,7.5mm		
PREL1	3501-001197	RELAY-MINIATURE;12VDC,0.54W,44.4mA,1Form		
PREL2	3501-001197	RELAY-MINIATURE;12VDC,0.54W,44.4mA,1Form		
PW4	3708-000181	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH		
JCW1	3708-000451	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH		
PW2	3710-001793	CONNECTOR-SOCKET;9P,1R,2.5MM,STRAIGHT,SN		
PW1	3710-001793	CONNECTOR-SOCKET;9P,1R,2.5MM,STRAIGHT,SN		
PCW1	3711-004989	CONNECTOR-HEADER;2WALL,9P,1R,2.5MM,ANGLE		
PCW2	3711-004989	CONNECTOR-HEADER;2WALL,9P,1R,2.5MM,ANGLE		
SPJACK	3716-001164	TERMINAL-BLOCK;SOLDER,8P,-,60V,7A		
	6003-001230	SCREW-TAPTITE;BH,+,B,M3,L16,ZPC(YEL),SWR		
PL7	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
PL6	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
PL5	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
PL4	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
PL3	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
PL2	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
PL1	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
PL8	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
PCW3	AH39-00295A	W/HARNESS UNIT;MAX-L85,-,-,9P,-,-,-,SCN-		
	AH60-10051A	SCREW-TAPTITE;-,-,FE,-,B,M3,L8,-,-,-		
	AH61-00973A	BRACKET-H/SINK,L;MAX-WB650,SECC T1.0,-,-		
	AH61-00977A	BRACKET-H/SINK,R;NAX-WB650,SECC T1.0,-,-		
	AH62-00063A	HEAT SINK-,M;MAX-WB650,AL EXTR,-,-,-,-		
PD5	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
PD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
PD3	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
PD2	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
PD1	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
PZD1	0403-000382	DIODE-ZENER;UZP15B,15V,13.9-15.6V,1W,DO-		
PZD2	0403-000382	DIODE-ZENER;UZP15B,15V,13.9-15.6V,1W,DO-		
PQ9	0501-000296	TR-SMALL SIGNAL;KSA709-Y,PNP,800mW,TO-92		
PQ6	0501-000296	TR-SMALL SIGNAL;KSA709-Y,PNP,800mW,TO-92		
PQ10	0501-000296	TR-SMALL SIGNAL;KSA709-Y,PNP,800mW,TO-92		
PQ8	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-9		
PQ5	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-9		
PQ16	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-		
PQ17	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-		
PQ4	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
PQ3	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
PQ2	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
PQ15	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
PQ1	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
PQ11	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
PQ12	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
PQ14	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
PQ7	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-		
PQ13	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-		
JLD5	0601-001238	LED;ROUND,RED,3.1mm,697nm		
JLD1	0601-001238	LED;ROUND,RED,3.1mm,697nm		
JLD10	0601-001238	LED;ROUND,RED,3.1mm,697nm		
JLD2	0601-001238	LED;ROUND,RED,3.1mm,697nm		
JLD3	0601-001238	LED;ROUND,RED,3.1mm,697nm		
JLD4	0601-001238	LED;ROUND,RED,3.1mm,697nm		
JLD6	0601-001238	LED;ROUND,RED,3.1mm,697nm		
JLD7	0601-001238	LED;ROUND,RED,3.1mm,697nm		
JLD8	0601-001238	LED;ROUND,RED,3.1mm,697nm		
JLD9	0601-001238	LED;ROUND,RED,3.1mm,697nm		
PR65	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR69	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
JR18	2001-000221	R-CARBON;1.2Kohm,5%,1/8W,AA,TP,1.8x3.2m		
JR21	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR28	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR36	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m		
JR1	2001-000258	R-CARBON;1.8Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR72	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR70	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR57	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR56	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR1	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR13	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR20	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR4	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR79	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		

Location no	Code no.	Description	Specifiation	Remarks
PR78	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR76	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR30	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
JR7	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR68	2001-000302	R-CARBON;10ohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR64	2001-000302	R-CARBON;10ohm,5%,1/8W,AA,TP,1.8x3.2mm		
JR20	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
JR21	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
JR4	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
JR5	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
JR6	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
JR11	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
JR12	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
JR13	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
JR14	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
JR15	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM		
PR51	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR81	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR82	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR84	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR85	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR50	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
JR19	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR15	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR18	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR19	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR24	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
JR2	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR77	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR74	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR67	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR63	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
JR9	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR62	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR66	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
JR3	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR53	2001-000660	R-CARBON;33Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR23	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR71	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR73	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR80	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR83	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
JR22	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
JR50	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR16	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR17	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR22	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR61	2001-000780	R-CARBON;470ohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR60	2001-000780	R-CARBON;470ohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR21	2001-000780	R-CARBON;470ohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR14	2001-000780	R-CARBON;470ohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR75	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR3	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR2	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		
PR49	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR52	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR54	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR55	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
JR10	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR27	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR29	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR35	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR37	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
JR8	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m		
JR17	2001-000995	R-CARBON;820ohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR11	2001-001000	R-CARBON;82Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR12	2001-001000	R-CARBON;82Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
PR40	2001-001077	R-CARBON(S);150ohm,5%,1/2W,AA,TP,2.4x6.4		
PR39	2001-001077	R-CARBON(S);150ohm,5%,1/2W,AA,TP,2.4x6.4		
PR25	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x		
PR26	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x		
PR44	2003-000428	R-METAL OXIDE(S);1.5Kohm,5%,1W,AA,TP,3.3		
PR43	2003-000428	R-METAL OXIDE(S);1.5Kohm,5%,1W,AA,TP,3.3		
PR9	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x		
PR8	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x		
PR7	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x		
PR38	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x		
PR10	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x		
PC13	2201-000300	C-CERAMIC,DISC;1nF,20%,50V,Y5T,TP,5x3,5		
PC12	2201-000300	C-CERAMIC,DISC;1nF,20%,50V,Y5T,TP,5x3,5		
PC29	2201-000338	C-CERAMIC,DISC;2.2nF,20%,50V,Y5T,TP,5.0x		
PC28	2201-000338	C-CERAMIC,DISC;2.2nF,20%,50V,Y5T,TP,5.0x		
PC51	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x		
PC52	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x		
PC53	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x		
PC58	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x		
PC57	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x		
PC56	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x		
PC55	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x		
PC54	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x		
PC62	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m		
PC61	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m		
PC60	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m		

Location no	Code no.	Description Specifiation	Remarks
PC59	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,-,-,12.5x4m	
PC26	2201-000674	C-CERAMIC,DISC;0.82nF,10%,50V,Y5P,BK,5x3	
PC27	2201-000674	C-CERAMIC,DISC;0.82nF,10%,50V,Y5P,BK,5x3	
PC3	2201-000783	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,	
PC35	2201-000838	C-CERAMIC,DISC;3pF,0.3pF,50V,CH,TP,5x3.5	
PC33	2201-000838	C-CERAMIC,DISC;3pF,0.3pF,50V,CH,TP,5x3.5	
PC14	2201-000838	C-CERAMIC,DISC;3pF,0.3pF,50V,CH,TP,5x3.5	
PC10	2201-000838	C-CERAMIC,DISC;3pF,0.3pF,50V,CH,TP,5x3.5	
JC2	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
JC1	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
PC38	2202-000806	C-CERAMIC,MLC-AXIAL;220pF,10%,50V,Y5P,TP	
PC34	2202-000806	C-CERAMIC,MLC-AXIAL;220pF,10%,50V,Y5P,TP	
PC15	2202-000806	C-CERAMIC,MLC-AXIAL;220pF,10%,50V,Y5P,TP	
PC11	2202-000806	C-CERAMIC,MLC-AXIAL;220pF,10%,50V,Y5P,TP	
PC5	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
PC4	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
PC2	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
PC7	2301-000379	C-FILM,PEF;10nF,10%,50V,TP,6x12x3.5mm,-	
PC16	2301-000379	C-FILM,PEF;10nF,10%,50V,TP,6x12x3.5mm,-	
PC9	2401-000357	C-AL;100uF,20%,50V,GP,-,8x11.5,3.5m	
PC50	2401-000357	C-AL;100uF,20%,50V,GP,-,8x11.5,3.5m	
PC21	2401-000357	C-AL;100uF,20%,50V,GP,-,8x11.5,3.5m	
PC20	2401-000357	C-AL;100uF,20%,50V,GP,-,8x11.5,3.5m	
PC19	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm	
PC18	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm	
PC63	2401-000970	C-AL;22uF,20%,50V,WT,TP,5x11,5	
PC8	2401-001164	C-AL;33uF,20%,16V,GP,TP,5x11mm,5mm	
PC17	2401-001164	C-AL;33uF,20%,16V,GP,TP,5x11mm,5mm	
PC64	2401-001538	C-AL;47uF,20%,25V,GP,TP,5x11mm,5mm	
PC37	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5	
PC36	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5	
PC1	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5	
PC32	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
PC31	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
JSW4	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW5	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW6	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW7	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW8	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW9	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW3	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW1	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW10	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW11	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW2	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW13	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW12	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
PCB	AH41-00449A	PCB-PCB AMP;MAX-WB650/VB630/675,-,-,-,1.	

***** MAXZB630 PARTS LIST *****

	3721-000117	PLUG-CONVERSION;2P,4.0PI,#16-22,SN
	3809-000171	CABLE-FLAT;30V,80C,200mm,16P,1.25mm,UL28
	3809-001034	CABLE-FLAT;30V,80C,170mm,22P,1.25mm,UL28
	3809-001185	CABLE-FLAT;30V,80C,120MM,16P,1.25MM,UL28
	3809-001222	CABLE-FLAT;30V,80C,50mm,11P,1.25mm,UL289
	3809-001332	CABLE-FLAT;30V,80C,140MM,16P,1.25MM,UL28
	AH26-00177A	TRANS POWER;-,MAX-B630,-,-,120/240V,-,-
	AH38-10001A	WIRE-LEAD;1007#22,1500MM
	AH39-00257A	POWER CORD;Z-88,-,CP2,250V,2.5A,1830MM/1
	AH39-50001X	WIRE HARNESS;RING,1007#24,200MM,BLK
	AH40-00010A	TUNER-PACK ASSY;-,FM/MW,-,-,-,-,-,75 O
	AH42-20001P	ANT LOOP;-,KS971120-01,18.5UH##10%,-
	AH59-00134N	REMOCON-ASSY;MAX-WB650,SAMSUNG,-,-,27KEY

AH59-00164B DECK-ASS'Y;-,MAX-ZL45,-,-,-,-,-,-

AH92-00922C ASSY PCB-CD,MP3;G3HI-3CD,MP3,3.5S

WIC402	1003-001162	IC-MOTOR DRIVER;KA3082,SIP,10PIN,25MIL,D
WIC401	1003-001162	IC-MOTOR DRIVER;KA3082,SIP,10PIN,25MIL,D
X201	2802-000211	RESONATOR-CERAMIC;16.93MHz,0.5%,TP,10.0x
CW103	3708-001131	CONNECTOR-FPC/FFC/PIC;5P,1.25mm,STRAIGHT
CW101	3708-001252	CONNECTOR-FPC/FFC/PIC;16P,1mm,STRAIGHT-F
CW105	3708-001438	CONNECTOR-FPC/FFC/PIC;22P,1.25mm,ANGLE,S
CW107	3711-000906	CONNECTOR-HEADER;BOX,3P,1R,2mm,ANGLE,SN
CW104	3711-003379	CONNECTOR-HEADER;NOWALL,3P,1R,2.5mm,STRA
CW106	AH39-00060A	LEAD CONNECTOR ASSY;-,51015-08,51004-08,
CW102	AH39-20561P	LEAD CONNECTOR ASSY;-,5295,PHR,6P,150mm,
D301	0402-000151	DIODE-RECTIFIER;1N5392,100V,1.5A,DO-15,T
ZD301	0403-000344	DIODE-ZENER;UZ3.9B,3.9V,3.7-4.1V,500mW,D
ZD402	0403-000352	DIODE-ZENER;UZ4.7BM,4.7V,4.4-5.0V,500mW,
ZD401	0403-000361	DIODE-ZENER;UZ6.2BSB,6.2V,5.99-6.24V,500
Q302	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,
Q101	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,
Q301	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,
WIC201	0904-001524	IC-DSP;SL9290,-,QFP,48P,472MIL,16.934
WIC301	1003-000179	IC-MOTOR DRIVER;KA9258D,SOP,28P,-,SINGLE
WIC602	1105-001339	IC-DRAM;11L1644,4Mx4Bit,TSOP,24P,300Mil
WIC101	1204-001799	IC-ASP;KB9226,LQFP,48P,393MIL,PLASTIC
WIC601	1204-001885	IC-DECODER;S5L9276,LQFP,64P,-,PLASTIC,3.
R117	2001-000331	R-CARBON;12Kohm,5%,1/8W,AA,TP,1.8x3.2mm

Location no	Code no.	Description Specifiation	Remarks
R810	2001-000362	R-CARBON;150ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R803	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R605	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R212	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R211	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R604	2001-000515	R-CARBON;220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R302	2001-001006	R-CARBON;82ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R114	2007-000001	R-CHIP;68KOHM,5%,1/10W,DA,TP,2012	
J3	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J4	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J5	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J7	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J8	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J9	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J1	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J10	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J11	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J13	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J14	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J2	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
R501R	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
R501L	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
R502R	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
R502L	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
R203	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
R201	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
R809	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R133	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R132	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R108	2007-000308	R-CHIP;10OHM,5%,1/10W,DA,TP,2012	
R125	2007-000338	R-CHIP;120KOHM,5%,1/10W,DA,TP,2012	
R124	2007-000338	R-CHIP;120KOHM,5%,1/10W,DA,TP,2012	
R110	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
R105	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
R121	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
R113	2007-000444	R-CHIP;180KOHM,5%,1/10W,DA,TP,2012	
R603	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R801	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R802	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R804	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R805	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R806	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R811	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R812	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R602	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R204	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R205	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R206	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R207	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R601	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R213	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R209	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R208	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R202	2007-000477	R-CHIP;1MOHM,5%,1/10W,DA,TP,2012	
R118	2007-000477	R-CHIP;1MOHM,5%,1/10W,DA,TP,2012	
R116	2007-000546	R-CHIP;20KOHM,5%,1/10W,DA,TP,2012	
R210	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
R128	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
R809	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
R808	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
R807	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
DR2	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
DR1	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
R813	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R129	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R123	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R126	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R120	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R104	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R103	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R102	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R101	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R115	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
R112	2007-001195	R-CHIP;820KOHM,5%,1/10W,DA,TP,2012	
R127	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
R119	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
R106	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
R105	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
R107	2007-001216	R-CHIP;82OHM,5%,1/10W,DA,TP,2012	
R301	2008-000140	R-FUSIBLE;2.2ohm,5%,1/2W,AA,TP,3.5x9.4mm	
C804	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
C805	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
C806	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
C603A	2202-000780	C-CERAMIC,MLC-AXIAL;100nF,+80-20%,50V,Y5	
C113	2202-000780	C-CERAMIC,MLC-AXIAL;100nF,+80-20%,50V,Y5	
C604	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C403	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C211	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C205	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C606	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C607	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C610	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C611	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	

Location no	Code no.	Description	Specifiation	Remarks
C612	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012		
C115	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012		
C116	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012		
C118	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012		
C124	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012		
C129	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012		
C204	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012		
C132	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012		
C131	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012		
C130	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012		
C305	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012		
C304	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012		
C218	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012		
C401	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012		
C402	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012		
C601	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012		
C602	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012		
C121	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012		
C134	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012		
C207	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012		
C209	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012		
C213	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012		
C214	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012		
C216	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012		
C126	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,2012		
C127	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012		
C803	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012		
C128	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012		
C119	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012		
C105	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012		
C125	2203-000840	C-CERAMIC,CHIP;0.39nF,5%,50V,NP0,TP,2012		
C208	2203-000858	C-CERAMIC,CHIP;0.039nF,5%,50V,NP0,TP,201		
C112	2203-000892	C-CERAMIC,CHIP;4.7NF,10%,50V,X7R,TP,2012		
C111	2203-000892	C-CERAMIC,CHIP;4.7NF,10%,50V,X7R,TP,2012		
C124A	2203-001064	C-CERAMIC,CHIP;56NF,10%,50V,NPO,TP,2012		
C122	2203-001137	C-CERAMIC,CHIP;68nF,+80-20%,50V,Y5V,TP,2		
C106	2203-001137	C-CERAMIC,CHIP;68nF,+80-20%,50V,Y5V,TP,2		
C608	2203-001223	C-CERAMIC,CHIP;0.82nF,10%,50V,X7R,TP,201		
C605	2203-001223	C-CERAMIC,CHIP;0.82nF,10%,50V,X7R,TP,201		
C203	2203-001223	C-CERAMIC,CHIP;0.82nF,10%,50V,X7R,TP,201		
C502R	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012		
C502L	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012		
C117	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012		
C102	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012		
C104	2203-001551	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,2012		
C103	2203-001551	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,2012		
C202	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,201		
C201	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,201		
C215	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C217	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C302	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C303	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C603	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C101	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C107	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C108	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C133	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C212	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
C123	2401-000419	C-AL;10UF,20%,16V,GP,-,5X11,5		
C801	2401-000795	C-AL;220uF,20%,16V,GP,TP,8x12mm,5mm		
C301	2401-001102	C-AL;330uF,20%,16V,GP,TP,8x11.5mm,5		
c114	2401-001625	C-AL;6.8uF,20%,50V,GP,TP,5x11,5		
C501L	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm		
C501R	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm		
C135	2401-001968	C-AL;470nF,20%,50V,GP,TP,5x11mm,5mm		
C120	2401-001968	C-AL;470nF,20%,50V,GP,TP,5x11mm,5mm		
WIC801	AC14-12001G	IC;KA78L05,T,-		
	AH92-01253A	ASSY PCB;G3HI-3CD/MP3		
	AJ59-20150F	DECK-LDP;CVM55R2/EXP,-,-,-,-		
	3710-000544	CONNECTOR-SOCKET;42140-2203 3P ,1R,2.5MM		
	3711-000826	CONNECTOR-HEADER;BOX,2P,1R,2mm,ANGLE,SN		
	AH91-60150C	ASSY CDP DECK;CMS-D73SG6(U)/JVC,CMS-300D		
	3409-001078	SWITCH-LEAF;16Vdc,500mA,10gf,SPST		
	AH30-00007A	PICK UP;SOH-AD3,-,-,-,100*80*45,D73SG6		
	AH59-01075B	SPEAKER SYSTEM;PSWB630E,-,-,-,-,-,-,XAP,		
	AH68-01034J	MANUAL USERS;MAX-WB650,ELS,POR,-,80G PAP		
	AH68-01034K	MANUAL USERS;MAX-WB650,MAC,ENG,-,80G PAP		
	AH68-01094J	MANUAL-BOOK;MAX-ZB630,MAC(NO RDS),ENG,-,		
	AH68-01094K	MANUAL-BOOK;MAX-ZB630,SMT,GSP(NO RDS),SP		

AH92-01375G ASSY PCB-FRONT;MAX-WB650LH,NO MIC,NO CE,

UIC2	0904-001621	IC-I/O CONTROLLER;PT8300,16BIT,SOP,28P,3		
UIC3	0904-001621	IC-I/O CONTROLLER;PT8300,16BIT,SOP,28P,3		
MIC1	1201-001572	IC-PREAMP;2011,SIP,7P,17MIL,SINGLE,47,PL		
MVR1	2101-001052	VR-ROTARY;10KOHM,10%,0.05W,TOP		
UX2	2801-001394	CRYSTAL-UNIT;32.768KHz,20ppm,28-AAY,12.5		
UX1	2802-001174	RESONATOR-CERAMIC;10MHZ,0.5%,BK,8X3.5X3M		
UVR1	3406-001047	SWITCH-ROTARY;5V DC,0.5mA,-,12mm		
UVR3	3406-001047	SWITCH-ROTARY;5V DC,0.5mA,-,12mm		
UVR2	3406-001050	SWITCH-ROTARY;5V DC,0.5mA,click,12mm		
UCW5	3708-000451	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH		
UCW4	3708-000451	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH		
UCW2	3708-000451	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH		
UCW1	3708-000451	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH		
UCW7	3708-000454	CONNECTOR-FPC/FFC/PIC;22P,1.25mm,STRAIGH		
UCW6	3708-000454	CONNECTOR-FPC/FFC/PIC;22P,1.25mm,STRAIGH		
UCW3	3708-000454	CONNECTOR-FPC/FFC/PIC;22P,1.25mm,STRAIGH		
UCH1	3711-000827	CONNECTOR-HEADER;BOX,2P,1R,2mm,STRAIGHT,		
UCH2	3711-001018	CONNECTOR-HEADER;BOX,5P,1R,2mm,STRAIGHT,		
HJACK1	3722-000351	JACK-PHONE;11P,3.5PI,AG,BLK,-		
MJACK2	3722-001190	JACK-PHONE;9P/2C,6.43PI,AU,BLK,RC6701(EI		
MJACK1	3722-001190	JACK-PHONE;9P/2C,6.43PI,AU,BLK,RC6701(EI		
RE-EYE	AC59-60060A	MODULE REMOCON;GP1U281R,SHARP,38KHZ,-,-,		
UVFD1	AH07-00066A	VF DISPLAY;HNA-16LM24T,MAX-B550/570/VB55		
UIC1	AH11-00074D	MASK ROM;LC876756A-50E1,MAX-WB630/WB650		
UCA2	AH39-00101A	LEAD CONNECTOR ASSY;-,5295,51004,5P,150M		
UCA1	AH39-00109A	LEAD CONNECTOR ASSY;-,5295,51004,2P,140M		
	AH39-50001L	WIRE HARNESS;RING,1007#24,200MM,BLK		
	AH39-50001N	WIRE HARNESS;RING,1007#24,250MM,BLK		
UD3	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
UD22	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
UD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
MD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
UD17	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
UD18	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		
UD21	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD23	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD27	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD30	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD15	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD16	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD19	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD20	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UZD2	0403-000393	DIODE-ZENER;UZP5.1B,5.1V,4.8-5.4V,1W,DO-		
UZD1	0403-000393	DIODE-ZENER;UZP5.1B,5.1V,4.8-5.4V,1W,DO-		
UQ2	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T		
UQ1	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T		
UQ6	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
UQ5	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
UQ4	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
UQ3	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
UQ9	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,		
UQ8	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,		
UQ7	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,		
UQ12	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-		
UQ11	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-		
ULD4	0601-001238	LED;ROUND,RED,3.1mm,697nm		
ULD3	0601-001238	LED;ROUND,RED,3.1mm,697nm		
ULD2	0601-001238	LED;ROUND,RED,3.1mm,697nm		
ULD1	0601-001238	LED;ROUND,RED,3.1mm,697nm		
MR5	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR91	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR69	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR62	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR130	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR150	2001-000027	R-CARBON;100ohm,5%,1/4W,AA,TP,2.4x6.4mm		
UR106	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4		
UR107	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4		
UR90	2001-000221	R-CARBON;1.2Kohm,5%,1/8W,AA,TP,1.8x3.2m		
UR129	2001-000221	R-CARBON;1.2Kohm,5%,1/8W,AA,TP,1.8x3.2m		
UR118	2001-000221	R-CARBON;1.2Kohm,5%,1/8W,AA,TP,1.8x3.2m		
UR112	2001-000258	R-CARBON;1.8Kohm,5%,1/8W,AA,TP,1.8x3.2m		
MR40	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m		
MR3	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR186	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR63	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR64	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR65	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR74	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR75	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR76	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR77	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR78	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR170	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR171	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR172	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR173	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR174	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR183	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR182	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR178	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR175	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR54	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR5	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR43	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR6	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR7	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR70	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR71	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR42	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR27	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR28	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR3	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR39	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR4	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		

Location no	Code no.	Description Specifiation Remarks
UR40	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR41	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR86	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR87	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR9	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR92	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR93	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR94	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR95	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR85	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR72	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR73	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR8	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR80	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR81	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR82	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR84	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR26	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR121	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR122	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR13	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR135	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR137	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR138	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR139	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR120	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
MR21	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR1	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR10	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR100	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR101	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR11	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR12	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR179	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR180	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR181	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR2	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR23	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR24	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR25	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR176	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR14	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR140	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR141	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR142	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR143	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR15	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR16	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR21	2001-000295	R-CARBON;10MOHM,5%,1/8W,AA,TP,1.8X3.2MM
UR19	2001-000362	R-CARBON;150ohm,5%,1/8W,AA,TP,1.8x3.2mm
UR133	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM
UR131	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM
UR111	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM
UR109	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM
UR108	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM
UR89	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR128	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR22	2001-000435	R-CARBON;1Mohm,5%,1/8W,AA,TP,1.8x3.2mm
MR4	2001-000435	R-CARBON;1Mohm,5%,1/8W,AA,TP,1.8x3.2mm
UR88	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m
UR17	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m
UR110	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m
MR6	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m
MR2	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m
UR18	2001-000508	R-CARBON;220Kohm,5%,1/8W,AA,TP,1.8x3.2m
UR44	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR124	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR145	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m
UR52	2001-000613	R-CARBON;3.9Kohm,5%,1/8W,AA,TP,1.8x3.2m
UR68	2001-000660	R-CARBON;33Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR61	2001-000660	R-CARBON;33Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR46	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m
UR51	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m
UR53	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m
UR55	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m
UR56	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m
UR57	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m
HR1	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m
HR2	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m
MR1	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m
UR146	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m
UR132	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m
MR7	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m
UR33	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR34	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR35	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR36	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR37	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR38	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR32	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm
MR20	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR134	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR200	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm

Location no	Code no.	Description Specifiation Remarks
UR31	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR30	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR29	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR20	2001-000850	R-CARBON;560Kohm,5%,1/8W,AA,TP,1.8x3.2m
UR119	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m
UR127	2001-000995	R-CARBON;820ohm,5%,1/8W,AA,TP,1.8x3.2mm
UR113	2001-000995	R-CARBON;820ohm,5%,1/8W,AA,TP,1.8x3.2mm
UR58	2001-001192	R-CARBON(S);820ohm,5%,1/2W,AA,TP,2.4x6.4
UR59	2001-001192	R-CARBON(S);820ohm,5%,1/2W,AA,TP,2.4x6.4
UR60	2001-001192	R-CARBON(S);820ohm,5%,1/2W,AA,TP,2.4x6.4
URV1	2103-000492	VR-SEMI;5Kohm,30%,1/10W,TOP
HC1	2201-000300	C-CERAMIC,DISC;1nF,20%,50V,Y5T,TP,5x3,5
HC2	2201-000300	C-CERAMIC,DISC;1nF,20%,50V,Y5T,TP,5x3,5
UC11	2201-000300	C-CERAMIC,DISC;1nF,20%,50V,Y5T,TP,5x3,5
UC8	2201-000389	C-CERAMIC,DISC;0.022nF,5%,50V,NP0,TP,5x3
UC7	2201-000389	C-CERAMIC,DISC;0.022nF,5%,50V,NP0,TP,5x3
ZC2	2201-000565	C-CERAMIC,DISC;47nF,+80% -20% 50V Y5V 12
ZC1	2201-000565	C-CERAMIC,DISC;47nF,+80% -20% 50V Y5V 12
UC35	2201-000565	C-CERAMIC,DISC;47nF,+80% -20% 50V Y5V 12
UC3	2201-000565	C-CERAMIC,DISC;47nF,+80% -20% 50V Y5V 12
UC15	2201-000565	C-CERAMIC,DISC;47nF,+80% -20% 50V Y5V 12
UC10	2201-000565	C-CERAMIC,DISC;47nF,+80% -20% 50V Y5V 12
UC1	2201-000565	C-CERAMIC,DISC;47nF,+80% -20% 50V Y5V 12
UC17	2201-000783	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,
UC60	2202-000780	C-CERAMIC,MLC-AXIAL;100nF,+80-20%,50V,Y5
UC25	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3
UC24	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3
UC21	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3
UC20	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3
UC19	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3
UC18	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3
ZC3	2202-000854	C-CERAMIC,MLC-AXIAL;47nF,30%,50V,Y5R,TP,
UC5	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7,5
UC4	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7,5
UC36	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7,5
UC16	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7,5
UC14	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7,5
UC100	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7,5
MC10	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7,5
UC9	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm
UC2	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm
MC4	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm
MC5	2401-001022	C-AL;3.3UF,20%,50V,GP,TP,5X11,5
UC13	2401-001355	C-AL;470uF,20%,10V,GP,TP,8x11.5mm,5
UC27	2401-001895	C-AL;100uF,20%,16V,GP,6.3*11,5MM,TP
UC26	2401-001895	C-AL;100uF,20%,16V,GP,6.3*11,5MM,TP
MC1	2401-001895	C-AL;100uF,20%,16V,GP,6.3*11,5MM,TP
MC6	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP
MC3	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP
UC12	2401-001919	C-AL;2.2uF,20%,50V,GP,4*7,5MM,TP
UC6	2401-001931	C-AL;220nF,20%,50V,-,TP,4x7mm,5
MC2	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm
MC30	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm
HL1	2701-000111	INDUCTOR-AXIAL;100uH,10%,2.5x3.4mm
HL2	2701-000111	INDUCTOR-AXIAL;100uH,10%,2.5x3.4mm
HR2	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm
HR1	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm
USW5	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST
USW4	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST
USW3	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST
USW2	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST
USW6	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST
USW7	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST
USW8	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST
USW9	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST
USW17	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST
USW1	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST
USW10	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST
USW11	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST
USW12	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST
USW16	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST
USW15	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST
USW14	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST
USW13	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST

AH92-01385C ASSY PCB-MAIN;MAX-WB630,MAIN ASSY,NO CE,

RBD1	0402-001258	DIODE-BRIDGE;GBU606,600V,6A,SIP-4,BK
RBD2	0402-001258	DIODE-BRIDGE;GBU606,600V,6A,SIP-4,BK
WIC2	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV
WIC1	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV
KIC1	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV
FIC1	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV
DIC1	1201-001819	IC-PREAMP;-,-,44P,-,-,-,PLASTIC,18V,625M
RIC1	1203-001653	IC-VOLTAGE REGULATOR;4959,MULTIWATT,15P,
KIC2	1204-001730	IC-ECHO;M65855P,DIP,16P,300MIL,PLASTIC
FIC2	1204-001776	IC-SOUND PROCESSOR;TDA7442D,SOP,28P,295M
RR34	2003-000005	R-METAL OXIDE(S);1ohm,5%,2W,AA,TP,4x12mm
RR9	2003-000455	R-METAL OXIDE(S);100ohm,5%,2W,AA,TP,4x12
RR3	2003-000701	R-METAL OXIDE(S);470ohm,5%,2W,AA,TP,4x12
RC19	2201-000546	C-CERAMIC,DISC;4.7nF,20%,400V,Y5U,BK,16x
RC18	2201-000546	C-CERAMIC,DISC;4.7nF,20%,400V,Y5U,BK,16x
CC3	2401-000129	C-AL;1000uF,20%,16V,GP,-,10x16mm,5
RC5	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm

Location no	Code no.	Description Specifiation	Remarks
RC14	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm	
RC2	2401-003381	C-AL;3300uF,20%,63V,GP,BK,22x40,10	
RC1	2401-003381	C-AL;3300uF,20%,63V,GP,BK,22x40,10	
RC3	2401-003755	C-AL;6800UF,20%,35V,BP,TP,22X40MM,1	
RC4	2401-003755	C-AL;6800UF,20%,35V,BP,TP,22X40MM,1	
RSW1	3408-000177	SWITCH-SLIDE;250V,5A,DPDT,<ON>-OFF-	
RF2	3601-000170	FUSE-CARTRIDGE;250V,1.6A,TIME-LAG,GLASS,	
RF1	3601-000263	FUSE-CARTRIDGE;250V,3.15A,TIME-LAG,GLASS	
FCW4	3708-000181	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH	
FCW2	3708-000181	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH	
FCW1	3708-000181	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH	
RCW2	3711-000190	CONNECTOR-HEADER;1WALL,2P,1R,7.92mm,STRA	
DCW2	3711-000907	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,	
CCW1	3711-001137	CONNECTOR-HEADER;BOX,8P,1R,2mm,STRAIGHT,	
RCW1	3711-003075	CONNECTOR-HEADER;NOWALL,6P,1R,8mm,STRAIG	
DCW3	3711-003107	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
DCW1	3711-003111	CONNECTOR-HEADER;BOX,6P,1R,2.5mm,STRAIGH	
RCW5	3711-003112	CONNECTOR-HEADER;BOX,8P,1R,2.5mm,STRAIGH	
ACW1	3711-003113	CONNECTOR-HEADER;BOX,9P,1R,2.5mm,STRAIGH	
AJCK	3722-000377	JACK-PIN;4P/2C,3.5mm,SN,BLK,#16~22	
DL1	AH26-10002W	TRANS TRAP-COIL;BIAS-TRAP105K,BIAS-TRAP,	
DL2	AH26-10002W	TRANS TRAP-COIL;BIAS-TRAP105K,BIAS-TRAP,	
DL4	AH26-10003C	TRANS TRAP-COIL;PCHNS-5371EQJ,BIAS-TRAP,	
WD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
TD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
TD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
KD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
DD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
FD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
KD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
RD2	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD13-1	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD12	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD1	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD11	0402-000151	DIODE-RECTIFIER;1N5392,100V,1.5A,DO-15,T	
WZD1	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,D	
RZD1	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,D	
KZD1	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,D	
FZD2	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,D	
FZD1	0403-000372	DIODE-ZENER;UZ9.1BM,9.1V,8.7-9.4V,500mW,	
RZD5	0403-000380	DIODE-ZENER;UZP13B,13V,12.4-14.1V,1W,DO-	
RZD3	0403-000564	DIODE-ZENER;TZP16A,16V,15.3-17.1V,1W,DO-	
RZD2	0403-000570	DIODE-ZENER;UZP18B,18V,16.9-19.1V,1W,DO-	
RZD4	0403-001010	DIODE-ZENER;UZP5.6B,5.6V,5.2-6.0V,1W,DO	
DQ9	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
DQ8	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
DQ7	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
DQ6	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
RQ2	0501-000294	TR-SMALL SIGNAL;KSA708-Y,PNP,800mW,TO-92	
CQ2	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-9	
CQ3	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-9	
DQ4	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
DQ1	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
FQ1	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
DQ5	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9	
DQ11	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9	
DQ10	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9	
DQ3	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,	
RQ1	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,	
KQ4	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	
KQ3	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	
KQ2	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	
DQ5	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-	
DQ40	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-	
CQ1	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-	
KR28	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
KR24	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR8	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR1	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
CR7	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
CR4	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR6	2001-000012	R-CARBON;680Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR8	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
FR11	2001-000027	R-CARBON;100ohm,5%,1/4W,AA,TP,2.4x6.4mm	
RR10	2001-000038	R-CARBON;390ohm,5%,1/4W,AA,TP,2.4x6.4mm	
WR50	2001-000109	R-CARBON(S);470ohm,5%,1/2W,AA,TP,2.4x6.4	
WR7	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR25	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR24	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m	
TR2	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR3	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR4	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR5	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR6	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR1	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR1	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR1	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR17	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR2	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR9	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR4	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR3	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR9	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	

Location no	Code no.	Description Specifiation	Remarks
KR26	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
KR23	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
KR20	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR3	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR24	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
KR25	2001-000319	R-CARBON;120Kohm,5%,1/8W,AA,TP,1.8x3.2m	
KR18	2001-000319	R-CARBON;120Kohm,5%,1/8W,AA,TP,1.8x3.2m	
TR9	2001-000331	R-CARBON;12Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR12	2001-000331	R-CARBON;12Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR18	2001-000362	R-CARBON;150ohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR4	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
KR30	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
KR14	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
KR13	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR10	2001-000435	R-CARBON;1Mohm,5%,1/8W,AA,TP,1.8x3.2mm	
KR31	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
KR15	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
KR12	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR17	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR13	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR6	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR16	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR23	2001-000456	R-CARBON;2.2ohm,5%,1/4W,AA,TP,2.4x6.4mm	
RR11	2001-000472	R-CARBON;2.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
WR3	2001-000515	R-CARBON;220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
KR21	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
KR29	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
KR7	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
KR8	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR10	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR12	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR25	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR27	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR5	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR9	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
TR8	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR12	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR7	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR14	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR4	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR5	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR7	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
WR5	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR2	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
CR1	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR20	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR21	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR28	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR6	2001-000613	R-CARBON;3.9Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR16	2001-000613	R-CARBON;3.9Kohm,5%,1/8W,AA,TP,1.8x3.2m	
CR5	2001-000613	R-CARBON;3.9Kohm,5%,1/8W,AA,TP,1.8x3.2m	
CR2	2001-000613	R-CARBON;3.9Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR13	2001-000645	R-CARBON;330Kohm,5%,1/8W,AA,TP,1.8x3.2m	
MR8	2001-000660	R-CARBON;33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR4	2001-000702	R-CARBON;39Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR12	2001-000702	R-CARBON;39Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR29	2001-000702	R-CARBON;39Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR14	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR5	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
TR10	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
TR11	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
TR7	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
WR11	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR11	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
KR27	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
KR4	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
KR5	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
KR6	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
KR9	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR23	2001-000773	R-CARBON;470Kohm,5%,1/8W,AA,TP,1.8x3.2m	
KR16	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
KR17	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR20	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR12	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR13	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR2	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR6	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
CR3	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
CR6	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR19	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR14	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR15	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR3	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
WR30	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR9	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR10	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR21	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR20	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR37	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
KR4	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
KR5	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR7	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR36	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	

Location no	Code no.	Description Specifiation	Remarks
DR12	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR27	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR34	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR35	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DR33	2001-000924	R-CARBON;680ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR32	2001-000924	R-CARBON;680ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR31	2001-000924	R-CARBON;680ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR30	2001-000924	R-CARBON;680ohm,5%,1/8W,AA,TP,1.8x3.2mm	
KR19	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8x3.2m	
DR8	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8x3.2m	
DR26	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8x3.2m	
RR13	2001-001004	R-CARBON;82ohm,5%,1/4W,AA,TP,2.4x6.4mm	
KR22	2001-001004	R-CARBON;82ohm,5%,1/4W,AA,TP,2.4x6.4mm	
RR1	2001-001153	R-CARBON(S);47ohm,5%,1/2W,AA,TP,2.4x6.4m	
RR2	2001-001153	R-CARBON(S);47ohm,5%,1/2W,AA,TP,2.4x6.4m	
DSR2	2103-000248	VR-SEMI;200Kohm,30%,1/10W,TOP	
DSR1	2103-000248	VR-SEMI;200Kohm,30%,1/10W,TOP	
RC26	2201-000161	C-CERAMIC,DISC;10nF,+80-20%,500V,Y5V,TP,	
RC25	2201-000161	C-CERAMIC,DISC;10nF,+80-20%,500V,Y5V,TP,	
DC23	2201-000300	C-CERAMIC,DISC;1nF,20%,50V,Y5T,TP,5x3,5	
DC22	2201-000300	C-CERAMIC,DISC;1nF,20%,50V,Y5T,TP,5x3,5	
DC19	2201-000300	C-CERAMIC,DISC;1nF,20%,50V,Y5T,TP,5x3,5	
DC18	2201-000300	C-CERAMIC,DISC;1nF,20%,50V,Y5T,TP,5x3,5	
FC29	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
FC3	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
FC6	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
KC3	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
KC4	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
DC17	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
DC33	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
FC26	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
FC27	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
FC28	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
WC4	2201-000557	C-CERAMIC,DISC;0.47nF,10%,50V,SL,TP,8x3.	
DC29	2201-000674	C-CERAMIC,DISC;0.82nF,10%,50V,Y5P,BK,5x3	
DC1	2201-000674	C-CERAMIC,DISC;0.82nF,10%,50V,Y5P,BK,5x3	
KC18	2202-000780	C-CERAMIC,MLC-AXIAL;100nF,+80-20%,50V,Y5	
EMC1	2202-000780	C-CERAMIC,MLC-AXIAL;100nF,+80-20%,50V,Y5	
TC4	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
TC5	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
TC6	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
TC7	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
TC8	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
TC9	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
DC2	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
DC4	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
DC5	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
TC1	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
TC2	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
TC3	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
TC20	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
EMC2	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
KC17	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
KC20	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
EMC4	2202-000806	C-CERAMIC,MLC-AXIAL;220pF,10%,50V,Y5P,TP	
EMC3	2202-000806	C-CERAMIC,MLC-AXIAL;220pF,10%,50V,Y5P,TP	
KC19	2202-000809	C-CERAMIC,MLC-AXIAL;3.3nF,20%,16V,Y5R,-,	
KC10	2202-000829	C-CERAMIC,MLC-AXIAL;820pF,10%,50V,Y5P,3.	
KC16	2202-000854	C-CERAMIC,MLC-AXIAL;47nF,30%,50V,Y5R,TP,	
KC15	2202-000854	C-CERAMIC,MLC-AXIAL;47nF,30%,50V,Y5R,TP,	
FC16	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
FC17	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
FC32	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
KC2	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
KC5	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
WC5	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
DC10	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
DC25	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
DC26	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
FC15	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
FC13	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
DC7	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7	
KC12	2301-000379	C-FILM,PEF;10nF,10%,50V,TP,6x12x3.5mm,-	
KC11	2301-000379	C-FILM,PEF;10nF,10%,50V,TP,6x12x3.5mm,-	
DC24	2301-000379	C-FILM,PEF;10nF,10%,50V,TP,6x12x3.5mm,-	
DC11	2301-000379	C-FILM,PEF;10nF,10%,50V,TP,6x12x3.5mm,-	
DC16	2301-000404	C-FILM,PEF;2.2nF,10%,50V,TP,5.5x12x3mm,-	
DC15	2301-000404	C-FILM,PEF;2.2nF,10%,50V,TP,5.5x12x3mm,-	
DC14	2301-000404	C-FILM,PEF;2.2nF,10%,50V,TP,5.5x12x3mm,-	
DC13	2301-000407	C-FILM,PEF;2.7nF,10%,50V,TP,5.5x12x3mm,-	
WC9	2301-000412	C-FILM,PEF;22nF,10%,50V,TP,8x12x4mm,-	
DC8	2301-000412	C-FILM,PEF;22nF,10%,50V,TP,8x12x4mm,-	
DC31	2301-000412	C-FILM,PEF;22nF,10%,50V,TP,8x12x4mm,-	
KC19	2301-000422	C-FILM,PEF;3.3nF,10%,50V,TP,5.5x7x3mm,-	
KC13	2301-000442	C-FILM,PEF;4.7nF,10%,50V,TP,5.5x7x3mm,5m	
CC2	2301-000449	C-FILM,PEF;47nF,10%,50V,TP,9.5x12.5x5mm,	
FC11	2301-000454	C-FILM,PEF;5.6nF,10%,50V,TP,6x12x3,3.5mm	
FC12	2301-000454	C-FILM,PEF;5.6nF,10%,50V,TP,6x12x3,3.5mm	
KC14	2301-000474	C-FILM,PEF;8.2nF,10%,50V,TP,6.5x12x3.5,3	
RC6	2401-000357	C-AL;100UF,0.2,50V,GP,8*12,5MM,SSL	
CC5	2401-000419	C-AL;10UF,20%,16V,GP,-,5X11,5	
DC30	2401-000419	C-AL;10UF,20%,16V,GP,-,5X11,5	
RC9	2401-000438	C-AL;10uF,20%,25V,GP,-,5x11,5mm	

Location no	Code no.	Description Specifiation	Remarks
WC8	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm	
WC3	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm	
WC2	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm	
WC1	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm	
DC2	2401-000778	C-AL;220uF,20%,10V,GP,6.3x11,5MM,TP	
RC11	2401-000795	C-AL;220uF,20%,16V,GP,TP,8x12mm,5mm	
RC10	2401-000907	C-AL;22uF,20%,16V,GP,TP,5x11mm,5mm	
KC22	2401-000907	C-AL;22uF,20%,16V,GP,TP,5x11mm,5mm	
FC10	2401-000907	C-AL;22uF,20%,16V,GP,TP,5x11mm,5mm	
CC1	2401-000907	C-AL;22uF,20%,16V,GP,TP,5x11mm,5mm	
FC36	2401-001022	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
FC1	2401-001022	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
DC36	2401-001022	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
DC35	2401-001022	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
DC5	2401-001080	C-AL;330nF,20%,50V,GP,-,5x11,2mm	
FC25	2401-001238	C-AL;4.7uF,20%,25V,GP,3*5,2.5MM,TP	
FC24	2401-001324	C-AL;470nF,20%,50V,GP,BK,3x5,1mm	
RC8	2401-001625	C-AL;6.8uF,20%,50V,GP,TP,5x11,5	
KC23	2401-001895	C-AL;100uF,20%,16V,GP,6.3*11,5MM,TP	
FC5	2401-001895	C-AL;100uF,20%,16V,GP,6.3*11,5MM,TP	
CC4	2401-001895	C-AL;100uF,20%,16V,GP,6.3*11,5MM,TP	
FC31	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP	
FC8	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP	
FC9	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP	
RC7	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP	
DC20	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP	
FC22	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP	
FC23	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP	
FC30	2401-001912	C-AL;1uF,20%,50V,GP,5*11,5mm,TP	
FC4	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm	
FC33	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm	
FC2	2401-001954	C-AL;4.7uF,20%,50V,GP,TP,5x11mm,5mm	
DC32	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm	
DC21	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm	
DC12	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm	
FC18	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
FC19	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
KC21	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
KC6	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
KC9	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
DC9	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
DC27	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
DC28	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
DC34	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
DC6	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
DC8	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
CL1	2701-000116	INDUCTOR-AXIAL;10uH,10%,4.2x9.8mm	
CL2	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
DL3	2701-000298	INDUCTOR-AXIAL;470uH,10%,4.2x9.8mm	
RF2	3602-000147	FUSE-CLIP;250V,7.5A,30mohm	
RF1	3602-000147	FUSE-CLIP;250V,7.5A,30mohm	

AH92-01387B ASSY PCB-AMP;MAX-WB630,AMP ASSY,NO CE,23

PIC1	1201-001582	IC-POWER AMP;402-070,SIP,15P,-,DUAL,30dB	
PIC2	1201-001856	IC-POWER AMP;STK442-090,SIP,14P,233MIL,S	
PR42	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x	
PR41	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x	
PR34	2003-000390	R-METAL OXIDE(S);0.27OHM,5%,2W,AA,TP,	
PR33	2003-000390	R-METAL OXIDE(S);0.27OHM,5%,2W,AA,TP,	
PR32	2003-000390	R-METAL OXIDE(S);0.27OHM,5%,2W,AA,TP,	
PR31	2003-000390	R-METAL OXIDE(S);0.27OHM,5%,2W,AA,TP,	
PR6	2003-000578	R-METAL OXIDE(S);220ohm,5%,2W,AA,TP,4x12	
PR5	2003-000578	R-METAL OXIDE(S);220ohm,5%,2W,AA,TP,4x12	
PR59	2009-001117	R-METAL PLATE;0.1OHM,5%,5W,CL,BK,5X13X18	
PR58	2009-001117	R-METAL PLATE;0.1OHM,5%,5W,CL,BK,5X13X18	
PR48	2009-001117	R-METAL PLATE;0.1OHM,5%,5W,CL,BK,5X13X18	
PR45	2009-001117	R-METAL PLATE;0.1OHM,5%,5W,CL,BK,5X13X18	
PR46	2009-001117	R-METAL PLATE;0.1OHM,5%,5W,CL,BK,5X13X18	
PR47	2009-001117	R-METAL PLATE;0.1OHM,5%,5W,CL,BK,5X13X18	
PC25	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm	
PC24	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm	
PC23	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm	
PC22	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm	
JVR1	3406-001054	SWITCH-ROTARY;5V DC,0.5mA,-,7.5mm	
PREL2	3501-001197	RELAY-MINIATURE;12VDC,0.54W,44.4mA,1Form	
PREL1	3501-001197	RELAY-MINIATURE;12VDC,0.54W,44.4mA,1Form	
PW4	3708-000181	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH	
JCW1	3708-000451	CONNECTOR-FPC/FFC/PIC;16P,1.25mm,STRAIGH	
PW2	3710-001793	CONNECTOR-SOCKET;9P,1R,2.5MM,STRAIGHT,SN	
PW1	3710-001793	CONNECTOR-SOCKET;9P,1R,2.5MM,STRAIGHT,SN	
PCW1	3711-004989	CONNECTOR-HEADER;2WALL,9P,1R,2.5MM,ANGLE	
PCW2	3711-004989	CONNECTOR-HEADER;2WALL,9P,1R,2.5MM,ANGLE	
SPJACK	3716-001164	TERMINAL-BLOCK;SOLDER,8P,-,60V,7A	
PL8	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-	
PL7	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-	
PL6	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-	
PL5	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-	
PL1	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-	
PL2	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-	
PL3	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-	
PL4	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-	
PCW3	AH39-00295A	W/HARNESS UNIT;MAX-L85,-,-,9P,-,-,-,SCN-	
PD5	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	

Location no	Code no.	Description Specifiation	Remarks
PD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
PD3	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
PD2	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
PD1	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
PZD1	0403-000382	DIODE-ZENER;UZP15B,15V,13.9-15.6V,1W,DO-	
PZD2	0403-000382	DIODE-ZENER;UZP15B,15V,13.9-15.6V,1W,DO-	
PQ9	0501-000296	TR-SMALL SIGNAL;KSA709-Y,PNP,800mW,TO-92	
PQ6	0501-000296	TR-SMALL SIGNAL;KSA709-Y,PNP,800mW,TO-92	
PQ10	0501-000296	TR-SMALL SIGNAL;KSA709-Y,PNP,800mW,TO-92	
PQ5	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-9	
PQ8	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-9	
PQ17	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
PQ16	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
PQ15	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9	
PQ2	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9	
PQ3	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9	
PQ4	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9	
PQ1	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9	
PQ11	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9	
PQ12	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9	
PQ14	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9	
PQ7	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-	
PQ13	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-	
JLD5	0601-001238	LED;ROUND,RED,3.1mm,697nm	
JLD6	0601-001238	LED;ROUND,RED,3.1mm,697nm	
JLD7	0601-001238	LED;ROUND,RED,3.1mm,697nm	
JLD8	0601-001238	LED;ROUND,RED,3.1mm,697nm	
JLD9	0601-001238	LED;ROUND,RED,3.1mm,697nm	
JLD1	0601-001238	LED;ROUND,RED,3.1mm,697nm	
JLD10	0601-001238	LED;ROUND,RED,3.1mm,697nm	
JLD2	0601-001238	LED;ROUND,RED,3.1mm,697nm	
JLD3	0601-001238	LED;ROUND,RED,3.1mm,697nm	
JLD4	0601-001238	LED;ROUND,RED,3.1mm,697nm	
PR69	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR65	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR62	2001-000010	R-CARBON;68Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR66	2001-000010	R-CARBON;68Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR68	2001-000019	R-CARBON(S);10ohm,5%,1/2W,AA,TP,2.4x6.4m	
PR64	2001-000019	R-CARBON(S);10ohm,5%,1/2W,AA,TP,2.4x6.4m	
JR17	2001-000221	R-CARBON;1.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR36	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR30	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR28	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR1	2001-000258	R-CARBON;1.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR70	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR72	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR87	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR57	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR13	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR20	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR56	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR79	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR78	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR76	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR7	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR20	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR21	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR4	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR5	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR6	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR11	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR12	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR13	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR14	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR15	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
PR51	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR81	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR82	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR84	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR85	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR50	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR18	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR15	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR18	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR19	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR24	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR2	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR77	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR74	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR67	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR63	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR4	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR9	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR3	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR83	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR80	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR73	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR71	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR23	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR22	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR16	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR17	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR22	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	

Location no	Code no.	Description Specifiation	Remarks
PR61	2001-000780	R-CARBON;470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR60	2001-000780	R-CARBON;470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR21	2001-000780	R-CARBON;470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR14	2001-000780	R-CARBON;470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR75	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR86	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR3	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
PR49	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR52	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR54	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR55	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR10	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR27	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR29	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR35	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR40	2001-000869	R-CARBON;56ohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR8	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR16	2001-000995	R-CARBON;820ohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR12	2001-001000	R-CARBON;82Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR11	2001-001000	R-CARBON;82Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
PR25	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x	
PR26	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x	
PR44	2003-000428	R-METAL OXIDE(S);1.5Kohm,5%,1W,AA,TP,3.3	
PR43	2003-000428	R-METAL OXIDE(S);1.5Kohm,5%,1W,AA,TP,3.3	
PR9	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x	
PR8	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x	
PR7	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x	
PR38	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x	
PR10	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x	
PC13	2201-000300	C-CERAMIC,DISC;1nF,20%,50V,Y5T,TP,5x3,5	
PC12	2201-000300	C-CERAMIC,DISC;1nF,20%,50V,Y5T,TP,5x3,5	
PC28	2201-000338	C-CERAMIC,DISC;2.2nF,20%,50V,Y5T,TP,5.0x	
PC29	2201-000338	C-CERAMIC,DISC;2.2nF,20%,50V,Y5T,TP,5.0x	
PC15	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
PC11	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
PC57	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x	
PC55	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x	
PC52	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x	
PC51	2201-000547	C-CERAMIC,DISC;4.7nF,20%,500V,Y5T,TP,14x	
PC62	2201-000565	C-CERAMIC,DISC;47nF,+80% -20% 50V Y5V 12	
PC61	2201-000565	C-CERAMIC,DISC;47nF,+80% -20% 50V Y5V 12	
PC60	2201-000565	C-CERAMIC,DISC;47nF,+80% -20% 50V Y5V 12	
PC59	2201-000565	C-CERAMIC,DISC;47nF,+80% -20% 50V Y5V 12	
PC27	2201-000674	C-CERAMIC,DISC;0.82nF,10%,50V,Y5P,BK,5x3	
PC26	2201-000674	C-CERAMIC,DISC;0.82nF,10%,50V,Y5P,BK,5x3	
PC3	2201-000783	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,	
PC8	2201-000783	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,	
PC5	2201-000783	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,	
PC4	2201-000783	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,	
PC35	2201-000838	C-CERAMIC,DISC;3pF,0.3pF,50V,CH,TP,5x3.5	
PC33	2201-000838	C-CERAMIC,DISC;3pF,0.3pF,50V,CH,TP,5x3.5	
PC14	2201-000838	C-CERAMIC,DISC;3pF,0.3pF,50V,CH,TP,5x3.5	
PC10	2201-000838	C-CERAMIC,DISC;3pF,0.3pF,50V,CH,TP,5x3.5	
PC38	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
PC34	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
JC1	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
JC2	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
PC7	2301-000379	C-FILM,PEF;10nF,10%,50V,TP,6x12x3.5mm,-	
PC16	2301-000379	C-FILM,PEF;10nF,10%,50V,TP,6x12x3.5mm,-	
PC9	2401-000357	C-AL;100UF,0.2,50V,GP,8*12,5MM,SSL	
PC50	2401-000357	C-AL;100UF,0.2,50V,GP,8*12,5MM,SSL	
PC21	2401-000357	C-AL;100UF,0.2,50V,GP,8*12,5MM,SSL	
PC20	2401-000357	C-AL;100UF,0.2,50V,GP,8*12,5MM,SSL	
PC19	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm	
PC18	2401-000475	C-AL;10uF,20%,50V,GP,TP,5x11mm,5mm	
PC61	2401-000970	C-AL;22uF,20%,50V,WT,TP,5x11,5	
PC60	2401-001538	C-AL;47uF,20%,25V,GP,TP,5x11mm,5mm	
PC37	2401-001895	C-AL;100uF,20%,16V,GP,6.3*11,5MM,TP	
PC36	2401-001895	C-AL;100uF,20%,16V,GP,6.3*11,5MM,TP	
PC1	2401-001895	C-AL;100uF,20%,16V,GP,6.3*11,5MM,TP	
PC8	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm	
PC17	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm	
PC32	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
PC31	2401-002180	C-AL;2.2uF,20%,50V,GP,TP,5x11mm,5mm	
JSW4	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW5	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW6	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW7	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW8	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW9	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW3	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW1	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW10	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW11	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW2	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW13	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
JSW12	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
	AH97-00900M	ASSY-CA'DECK;-,RCD495/695/ST-68,ASSY CA'	
	3809-001188	CABLE-FLAT;30V,80C,240mm,16P,1.25mm,UL28	
	AH39-00021A	LEAD CONNECTOR ASSY;UL1533#28,300MM,-,-,	
	AH39-20002D	LEAD CONNECTOR ASSY;5264,-,3P,300MM,2970	
	AH59-00075A	DECK;ADR246AMW,1A/RVS,-,-,DC12V,-,-	